

### FEATURES

- Gain set with 1 external resistor
  - Gain range: 5 to 1000
- Input voltage goes below ground
- Inputs protected beyond supplies
- Very wide power supply range
  - Single supply: 2.2 V to 36 V
  - Dual supply:  $\pm 1.5$  V to  $\pm 18$  V
- Bandwidth (G = 5): 250 kHz
- CMRR (G = 5): 100 dB minimum (B Grade)
- Input noise: 24 nV/ $\sqrt{\text{Hz}}$
- Typical supply current: 350  $\mu\text{A}$
- Specified temperature:  $-40^{\circ}\text{C}$  to  $+125^{\circ}\text{C}$
- 8-lead SOIC and MSOP packages

### APPLICATIONS

- Industrial process controls
- Bridge amplifiers
- Medical instrumentation
- Portable data acquisition
- Multichannel systems

### GENERAL DESCRIPTION

The AD8227 is a low cost, wide supply range instrumentation amplifier that requires only one external resistor to set any gain between 5 and 1000.

The AD8227 is designed to work with a variety of signal voltages. A wide input range and rail-to-rail output allow the signal to make full use of the supply rails. Because the input range can also go below the negative supply, small signals near ground can be amplified without requiring dual supplies. The AD8227 operates on supplies ranging from  $\pm 1.5$  V to  $\pm 18$  V (2.2 V to 36 V single supply).

The robust AD8227 inputs are designed to connect to real-world sensors. In addition to its wide operating range, the AD8227 can handle voltages beyond the rails. For example, with a  $\pm 5$  V supply, the part is guaranteed to withstand  $\pm 35$  V at the input with no damage. Minimum as well as maximum input bias currents are specified to facilitate open wire detection.

### PIN CONFIGURATION




Figure 1.

07759-001

Table 1. Instrumentation Amplifiers by Category<sup>1</sup>

| General Purpose | Zero Drift | Military Grade | Low Power | High Speed PGA |
|-----------------|------------|----------------|-----------|----------------|
| AD8220          | AD8231     | AD620          | AD627     | AD8250         |
| AD8221          | AD8290     | AD621          | AD623     | AD8251         |
| AD8222          | AD8293     | AD524          | AD8223    | AD8253         |
| AD8224          | AD8553     | AD526          | AD8226    |                |
| AD8228          | AD8556     | AD624          | AD8227    |                |
| AD8295          | AD8557     |                |           |                |

<sup>1</sup> See [www.analog.com](http://www.analog.com) for the latest selection of instrumentation amplifiers.

The AD8227 is ideal for multichannel, space-constrained applications. With its MSOP package and  $125^{\circ}\text{C}$  temperature rating, the AD8227 thrives in tightly packed, zero airflow designs.

The AD8227 is available in 8-pin MSOP and SOIC packages. It is fully specified for  $-40^{\circ}\text{C}$  to  $+125^{\circ}\text{C}$  operation.

For a similar instrumentation amplifier with a gain range of 1 to 1000, see the [AD8226](#).

#### Rev. 0

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

## TABLE OF CONTENTS

|   |    |  |    |
|---|----|--|----|
| Features .....                                    | 1  | Gain Selection .....                     | 19 |
| Applications .....                                | 1  | Reference Terminal .....                 | 20 |
| Pin Configuration .....                           | 1  | Input Voltage Range .....                | 20 |
| General Description .....                         | 1  | Layout .....                             | 20 |
| Revision History .....                            | 2  | Input Bias Current Return Path .....     | 21 |
| Specifications .....                              | 3  | Input Protection .....                   | 21 |
| Absolute Maximum Ratings .....                    | 7  | Radio Frequency Interference (RFI) ..... | 21 |
| Thermal Resistance .....                          | 7  | Applications Information .....           | 22 |
| ESD Caution .....                                 | 7  | Differential Drive .....                 | 22 |
| Pin Configuration and Function Descriptions ..... | 8  | Precision Strain Gage .....              | 22 |
| Typical Performance Characteristics .....         | 9  | Driving an ADC .....                     | 23 |
| Theory of Operation .....                         | 19 | Outline Dimensions .....                 | 24 |
| Architecture .....                                | 19 | Ordering Guide .....                     | 24 |

## REVISION HISTORY

5/09—Revision 0: Initial Version

## SPECIFICATIONS

+V<sub>S</sub> = +15 V, -V<sub>S</sub> = -15 V, V<sub>REF</sub> = 0 V, T<sub>A</sub> = 25°C, G = 5, R<sub>L</sub> = 10 kΩ, specifications referred to input, unless otherwise noted.

Table 2.

| Parameter                             | Test Conditions/<br>Comments  | A Grade         |      |                 | B Grade         |      |                 | Unit   |
|---------------------------------------|---|-----------------|------|-----------------|-----------------|------|-----------------|--------|
|                                       |   | Min             | Typ  | Max             | Min             | Typ  | Max             |        |
| COMMON-MODE REJECTION RATIO           | V <sub>CM</sub> = -10 V to +10 V  |                 |      |                 |                 |      |                 |        |
| DC to 60 Hz                           |   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   | 90              |      |                 | 100             |      |                 | dB     |
| G = 10                                |   | 96              |      |                 | 105             |      |                 | dB     |
| G = 100                               |   | 105             |      |                 | 110             |      |                 | dB     |
| G = 1000                              |   | 105             |      |                 | 110             |      |                 | dB     |
| 5 kHz                                 |   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   | 80              |      |                 | 80              |      |                 | dB     |
| G = 10                                |   | 86              |      |                 | 86              |      |                 | dB     |
| G = 100                               |   | 86              |      |                 | 86              |      |                 | dB     |
| G = 1000                              |   | 86              |      |                 | 86              |      |                 | dB     |
| NOISE                                 | Total noise:<br>$e_N = \sqrt{(e_{NI}^2 + (e_{NO}/G)^2)}$                            |                 |      |                 |                 |      |                 |        |
| Voltage Noise, 1 kHz                  |   |                 |      |                 |                 |      |                 |        |
| Input Voltage Noise, e <sub>NI</sub>  |   |                 | 24   | 25              |                 | 24   | 25              | nV/√Hz |
| Output Voltage Noise, e <sub>NO</sub> |   |                 | 310  | 315             |                 | 310  | 315             | nV/√Hz |
| RTI                                   | f = 0.1 Hz to 10 Hz   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   |                 | 1.5  |                 |                 | 1.5  |                 | μV p-p |
| G = 10                                |   |                 | 0.9  |                 |                 | 0.9  |                 | μV p-p |
| G = 100 to 1000                       |   |                 | 0.5  |                 |                 | 0.5  |                 | μV p-p |
| Current Noise                         | f = 1 kHz<br>f = 0.1 Hz to 10 Hz  |                 | 100  |                 |                 | 100  |                 | fA/√Hz |
|                                       |   |                 | 3    |                 |                 | 3    |                 | pA p-p |
| VOLTAGE OFFSET                        | Total offset voltage:<br>V <sub>OS</sub> = V <sub>OSI</sub> + (V <sub>OSO</sub> /G) |                 |      |                 |                 |      |                 |        |
| Input Offset, V <sub>OSI</sub>        | V <sub>S</sub> = ±5 V to ±15 V  |                 |      | 200             |                 |      | 100             | μV     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 0.2  | 2               |                 | 0.2  | 1               | μV/°C  |
| Output Offset, V <sub>OSO</sub>       | V <sub>S</sub> = ±5 V to ±15 V  |                 |      | 1000            |                 |      | 500             | μV     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 2    | 10              |                 | 2    | 5               | μV/°C  |
| Offset RTI vs. Supply (PSR)           | V <sub>S</sub> = ±5 V to ±15 V  |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   | 90              |      |                 | 100             |      |                 | dB     |
| G = 10                                |   | 96              |      |                 | 105             |      |                 | dB     |
| G = 100                               |   | 105             |      |                 | 110             |      |                 | dB     |
| G = 1000                              |   | 105             |      |                 | 110             |      |                 | dB     |
| INPUT CURRENT                         |   |                 |      |                 |                 |      |                 |        |
| Input Bias Current <sup>1</sup>       | T <sub>A</sub> = +25°C  | 5               | 20   | 27              | 5               | 20   | 27              | nA     |
|                                       | T <sub>A</sub> = +125°C   | 5               | 15   | 25              | 5               | 15   | 25              | nA     |
|                                       | T <sub>A</sub> = -40°C  | 5               | 30   | 35              | 5               | 30   | 35              | nA     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 70   |                 |                 | 70   |                 | pA/°C  |
| Input Offset Current                  | T <sub>A</sub> = +25°C  |                 |      | 1.5             |                 |      | 1.5             | nA     |
|                                       | T <sub>A</sub> = +125°C   |                 |      | 1.5             |                 |      | 1.5             | nA     |
|                                       | T <sub>A</sub> = -40°C  |                 |      | 2               |                 |      | 2               | nA     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 5    |                 |                 | 5    |                 | pA/°C  |
| REFERENCE INPUT                       |   |                 |      |                 |                 |      |                 |        |
| R <sub>IN</sub>                       |   |                 | 60   |                 |                 | 60   |                 | kΩ     |
| I <sub>IN</sub>                       |   |                 | 12   |                 |                 | 12   |                 | μA     |
| Voltage Range                         |   | -V <sub>S</sub> |      | +V <sub>S</sub> | -V <sub>S</sub> |      | +V <sub>S</sub> | V      |
| Reference Gain to Output              |   |                 | 1    |                 |                 | 1    |                 | V/V    |
| Reference Gain Error                  |   |                 | 0.01 |                 |                 | 0.01 |                 | %      |

# AD8227

| Parameter                            | Test Conditions/<br>Comments      | A Grade                |     |                       | B Grade                |     |                       | Unit   |
|--------------------------------------|-----------------------------------|------------------------|-----|-----------------------|------------------------|-----|-----------------------|--------|
|                                      |                                   | Min                    | Typ | Max                   | Min                    | Typ | Max                   |        |
| <b>DYNAMIC RESPONSE</b>              |                                   |                        |     |                       |                        |     |                       |        |
| Small Signal –3 dB Bandwidth         |                                   |                        |     |                       |                        |     |                       |        |
| G = 5                                |                                   |                        | 250 |                       | 250                    |     |                       | kHz    |
| G = 10                               |                                   |                        | 200 |                       | 200                    |     |                       | kHz    |
| G = 100                              |                                   |                        | 50  |                       | 50                     |     |                       | kHz    |
| G = 1000                             |                                   |                        | 5   |                       | 5                      |     |                       | kHz    |
| Settling Time 0.01%                  | 10 V step                         |                        |     |                       |                        |     |                       |        |
| G = 5                                |                                   |                        | 14  |                       | 14                     |     |                       | μs     |
| G = 10                               |                                   |                        | 15  |                       | 15                     |     |                       | μs     |
| G = 100                              |                                   |                        | 35  |                       | 35                     |     |                       | μs     |
| G = 1000                             |                                   |                        | 275 |                       | 275                    |     |                       | μs     |
| Slew Rate <sup>2</sup>               | G = 5 to 100                      |                        | 0.8 |                       | 0.8                    |     |                       | V/μs   |
| <b>GAIN<sup>3</sup></b>              |                                   |                        |     |                       |                        |     |                       |        |
| Gain Range                           | G = 5 + (80 kΩ/R <sub>G</sub> )   | 5                      |     | 1000                  | 5                      |     | 1000                  | V/V    |
| Gain Error                           | V <sub>OUT</sub> = –10 V to +10 V |                        |     |                       |                        |     |                       |        |
| G = 5                                |                                   |                        |     | 0.04                  |                        |     | 0.02                  | %      |
| G = 10 to 1000                       |                                   |                        |     | 0.3                   |                        |     | 0.15                  | %      |
| Gain Nonlinearity                    | V <sub>OUT</sub> = –10 V to +10 V |                        |     |                       |                        |     |                       |        |
| G = 5                                | R <sub>L</sub> ≥ 2 kΩ             |                        |     | 10                    |                        |     | 10                    | ppm    |
| G = 10                               | R <sub>L</sub> ≥ 2 kΩ             |                        |     | 15                    |                        |     | 15                    | ppm    |
| G = 100                              | R <sub>L</sub> ≥ 2 kΩ             |                        |     | 15                    |                        |     | 50                    | ppm    |
| G = 1000                             | R <sub>L</sub> ≥ 2 kΩ             |                        |     | 750                   |                        |     | 150                   | ppm    |
| Gain vs. Temperature                 | T <sub>A</sub> = –40°C to +125°C  |                        |     |                       |                        |     |                       |        |
| G = 5                                |                                   |                        |     | 5                     |                        |     | 5                     | ppm/°C |
| G > 5                                |                                   |                        |     | –100                  |                        |     | –100                  | ppm/°C |
| <b>INPUT</b>                         |                                   |                        |     |                       |                        |     |                       |        |
| Impedance                            | V <sub>S</sub> = ±1.5 V to +36 V  |                        |     |                       |                        |     |                       |        |
| Differential                         |                                   |                        |     | 0.8  2                |                        |     | 0.8  2                | GΩ  pF |
| Common Mode                          |                                   |                        |     | 0.4  2                |                        |     | 0.4  2                | GΩ  pF |
| Operating Voltage Range <sup>4</sup> | T <sub>A</sub> = +25°C            | –V <sub>S</sub> – 0.1  |     | +V <sub>S</sub> – 0.8 | –V <sub>S</sub> – 0.1  |     | +V <sub>S</sub> – 0.8 | V      |
|                                      | T <sub>A</sub> = +125°C           | –V <sub>S</sub> – 0.05 |     | +V <sub>S</sub> – 0.6 | –V <sub>S</sub> – 0.05 |     | +V <sub>S</sub> – 0.6 | V      |
|                                      | T <sub>A</sub> = –40°C            | –V <sub>S</sub> – 0.15 |     | +V <sub>S</sub> – 0.9 | –V <sub>S</sub> – 0.15 |     | +V <sub>S</sub> – 0.9 | V      |
| Overvoltage Range                    | T <sub>A</sub> = –40°C to +125°C  | +V <sub>S</sub> – 40   |     | –V <sub>S</sub> + 40  | +V <sub>S</sub> – 40   |     | –V <sub>S</sub> + 40  | V      |
| <b>OUTPUT</b>                        |                                   |                        |     |                       |                        |     |                       |        |
| Output Swing                         |                                   |                        |     |                       |                        |     |                       |        |
| R <sub>L</sub> = 10 kΩ to ground     | T <sub>A</sub> = –40°C to +85°C   | –V <sub>S</sub> + 0.2  |     | +V <sub>S</sub> – 0.2 | –V <sub>S</sub> + 0.2  |     | +V <sub>S</sub> – 0.2 | V      |
|                                      | T <sub>A</sub> = +85°C to +125°C  | –V <sub>S</sub> + 0.2  |     | +V <sub>S</sub> – 0.3 | –V <sub>S</sub> + 0.2  |     | +V <sub>S</sub> – 0.3 | V      |
| R <sub>L</sub> = 100 kΩ to ground    | T <sub>A</sub> = –40°C to +125°C  | –V <sub>S</sub> + 0.1  |     | +V <sub>S</sub> – 0.1 | –V <sub>S</sub> + 0.1  |     | +V <sub>S</sub> – 0.1 | V      |
| Short-Circuit Current                |                                   |                        | 13  |                       |                        | 13  |                       | mA     |
| <b>POWER SUPPLY</b>                  |                                   |                        |     |                       |                        |     |                       |        |
| Operating Range                      | Dual-supply operation             | ±1.5                   |     | ±18                   | ±1.5                   |     | ±18                   | V      |
| Quiescent Current                    | T <sub>A</sub> = +25°C            |                        | 350 | 425                   |                        | 350 | 425                   | μA     |
|                                      | T <sub>A</sub> = –40°C            |                        | 250 | 325                   |                        | 250 | 325                   | μA     |
|                                      | T <sub>A</sub> = +85°C            |                        | 450 | 525                   |                        | 450 | 525                   | μA     |
|                                      | T <sub>A</sub> = +125°C           |                        | 525 | 600                   |                        | 525 | 600                   | μA     |
| <b>TEMPERATURE RANGE</b>             |                                   |                        |     |                       |                        |     |                       |        |
|                                      |                                   | –40                    |     | +125                  | –40                    |     | +125                  | °C     |

<sup>1</sup> The input stage uses pnp transistors, so input bias current always flows into the part.

<sup>2</sup> At high gains, the part is bandwidth limited rather than slew rate limited.

<sup>3</sup> For G > 5, gain error specifications do not include the effects of External Resistor R<sub>G</sub>.

<sup>4</sup> Input voltage range of the AD8227 input stage. The input range depends on the common-mode voltage, differential voltage, gain, and reference voltage. See the Input Voltage Range section for more information.

+V<sub>S</sub> = 2.7 V, -V<sub>S</sub> = 0 V, V<sub>REF</sub> = 0 V, T<sub>A</sub> = 25°C, G = 5, R<sub>L</sub> = 10 kΩ, specifications referred to input, unless otherwise noted.

Table 3.

| Parameter                             | Test Conditions/<br>Comments  | A Grade         |      |                 | B Grade         |      |                 | Unit   |
|---------------------------------------|---|-----------------|------|-----------------|-----------------|------|-----------------|--------|
|                                       |   | Min             | Typ  | Max             | Min             | Typ  | Max             |        |
| COMMON-MODE REJECTION RATIO           | V <sub>CM</sub> = 0 V to 1.7 V  |                 |      |                 |                 |      |                 |        |
| DC to 60 Hz                           |   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   | 90              |      |                 | 100             |      |                 | dB     |
| G = 10                                |   | 96              |      |                 | 105             |      |                 | dB     |
| G = 100                               |   | 105             |      |                 | 110             |      |                 | dB     |
| G = 1000                              |   | 105             |      |                 | 110             |      |                 | dB     |
| 5 kHz                                 |   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   | 80              |      |                 | 80              |      |                 | dB     |
| G = 10                                |   | 86              |      |                 | 86              |      |                 | dB     |
| G = 100                               |   | 86              |      |                 | 86              |      |                 | dB     |
| G = 1000                              |   | 86              |      |                 | 86              |      |                 | dB     |
| NOISE                                 | Total noise:<br>$e_N = \sqrt{(e_{NI}^2 + (e_{NO}/G)^2)}$                            |                 |      |                 |                 |      |                 |        |
| Voltage Noise, 1 kHz                  |   |                 |      |                 |                 |      |                 |        |
| Input Voltage Noise, e <sub>NI</sub>  |   |                 | 25   | 28              |                 | 25   | 28              | nV/√Hz |
| Output Voltage Noise, e <sub>NO</sub> |   |                 | 310  | 330             |                 | 310  | 330             | nV/√Hz |
| RTI                                   | f = 0.1 Hz to 10 Hz   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   |                 | 1.5  |                 |                 | 1.5  |                 | μV p-p |
| G = 10                                |   |                 | 0.8  |                 |                 | 0.8  |                 | μV p-p |
| G = 100 to 1000                       |   |                 | 0.5  |                 |                 | 0.5  |                 | μV p-p |
| Current Noise                         | f = 1 kHz<br>f = 0.1 Hz to 10 Hz  |                 | 100  |                 |                 | 100  |                 | fA/√Hz |
|                                       |   |                 | 3    |                 |                 | 3    |                 | pA p-p |
| VOLTAGE OFFSET                        | Total offset voltage:<br>V <sub>OS</sub> = V <sub>OSI</sub> + (V <sub>OSO</sub> /G) |                 |      |                 |                 |      |                 |        |
| Input Offset, V <sub>OSI</sub>        | V <sub>S</sub> = 0 V to 1.7 V   |                 |      | 200             |                 |      | 100             | μV     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 0.2  | 2               |                 | 0.2  | 1               | μV/°C  |
| Output Offset, V <sub>OSO</sub>       | V <sub>S</sub> = 0 V to 1.7 V   |                 |      | 1000            |                 |      | 500             | μV     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 2    | 10              |                 | 2    | 5               | μV/°C  |
| Offset RTI vs. Supply (PSR)           | V <sub>S</sub> = 0 V to 1.7 V   |                 |      |                 |                 |      |                 |        |
| G = 5                                 |   | 90              |      |                 | 100             |      |                 | dB     |
| G = 10                                |   | 96              |      |                 | 105             |      |                 | dB     |
| G = 100                               |   | 105             |      |                 | 110             |      |                 | dB     |
| G = 1000                              |   | 105             |      |                 | 110             |      |                 | dB     |
| INPUT CURRENT                         |   |                 |      |                 |                 |      |                 |        |
| Input Bias Current <sup>1</sup>       | T <sub>A</sub> = +25°C  | 5               | 20   | 27              | 5               | 20   | 27              | nA     |
|                                       | T <sub>A</sub> = +125°C   | 5               | 15   | 25              | 5               | 15   | 25              | nA     |
|                                       | T <sub>A</sub> = -40°C  | 5               | 30   | 35              | 5               | 30   | 35              | nA     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 70   |                 |                 | 70   |                 | pA/°C  |
| Input Offset Current                  | T <sub>A</sub> = +25°C  |                 |      | 1.5             |                 |      | 1.5             | nA     |
|                                       | T <sub>A</sub> = +125°C   |                 |      | 1.5             |                 |      | 1.5             | nA     |
|                                       | T <sub>A</sub> = -40°C  |                 |      | 2               |                 |      | 2               | nA     |
| Average Temperature Drift             | T <sub>A</sub> = -40°C to +125°C  |                 | 5    |                 |                 | 5    |                 | pA/°C  |
| REFERENCE INPUT                       |   |                 |      |                 |                 |      |                 |        |
| R <sub>IN</sub>                       |   |                 | 60   |                 |                 | 60   |                 | kΩ     |
| I <sub>IN</sub>                       |   |                 | 12   |                 |                 | 12   |                 | μA     |
| Voltage Range                         |   | -V <sub>S</sub> |      | +V <sub>S</sub> | -V <sub>S</sub> |      | +V <sub>S</sub> | V      |
| Reference Gain to Output              |   |                 | 1    |                 |                 | 1    |                 | V/V    |
| Reference Gain Error                  |   |                 | 0.01 |                 |                 | 0.01 |                 | %      |

# AD8227

| Parameter                            | Test Conditions/<br>Comments                           | A Grade              |        |                       | B Grade              |        |                       | Unit   |
|--------------------------------------|--|----------------------|--------|-----------------------|----------------------|--------|-----------------------|--------|
|                                      |  | Min                  | Typ    | Max                   | Min                  | Typ    | Max                   |        |
| <b>DYNAMIC RESPONSE</b>              |  |                      |        |                       |                      |        |                       |        |
| Small Signal –3 dB Bandwidth         | 2 V step   |                      |        |                       |                      |        |                       |        |
| G = 5                                |  |                      | 250    |                       | 250                  |        |                       | kHz    |
| G = 10                               |  |                      | 200    |                       | 200                  |        |                       | kHz    |
| G = 100                              |  |                      | 50     |                       | 50                   |        |                       | kHz    |
| G = 1000                             |  |                      | 5      |                       | 5                    |        |                       | kHz    |
| Settling Time 0.01%                  |  |                      |        |                       |                      |        |                       |        |
| G = 5                                |  |                      | 6      |                       | 6                    |        |                       | μs     |
| G = 10                               |  |                      | 6      |                       | 6                    |        |                       | μs     |
| G = 100                              |  |                      | 30     |                       | 30                   |        |                       | μs     |
| G = 1000                             |  |                      | 275    |                       | 275                  |        |                       | μs     |
| Slew Rate <sup>2</sup>               | G = 5 to 10  |                      | 0.6    |                       | 0.6                  |        | V/μs                  |        |
| <b>GAIN<sup>3</sup></b>              |  |                      |        |                       |                      |        |                       |        |
| Gain Range                           | G = 5 + (80 kΩ/R <sub>G</sub> )                        | 5                    |        | 1000                  | 5                    |        | 1000                  | V/V    |
| Gain Error                           |  |                      |        |                       |                      |        |                       |        |
| G = 5                                | V <sub>OUT</sub> = 0.8 V to 1.8 V                      |                      |        | 0.04                  |                      |        | 0.04                  | %      |
| G = 10 to 1000                       | V <sub>OUT</sub> = 0.2 V to 2.5 V                      |                      |        | 0.3                   |                      |        | 0.3                   | %      |
| Gain vs. Temperature                 | T <sub>A</sub> = –40°C to +125°C                       |                      |        |                       |                      |        |                       |        |
| G = 5                                |  |                      |        | 5                     |                      |        | 5                     | ppm/°C |
| G > 5                                |  |                      |        | –100                  |                      |        | –100                  | ppm/°C |
| <b>INPUT</b>                         |  |                      |        |                       |                      |        |                       |        |
|                                      | –V <sub>S</sub> = 0 V; +V <sub>S</sub> = 2.7 V to 36 V |                      |        |                       |                      |        |                       |        |
| Impedance                            |  |                      |        |                       |                      |        |                       |        |
| Differential                         |  |                      | 0.8  2 |                       |                      | 0.8  2 |                       | GΩ  pF |
| Common Mode                          |  |                      | 0.4  2 |                       |                      | 0.4  2 |                       | GΩ  pF |
| Operating Voltage Range <sup>4</sup> | T <sub>A</sub> = +25°C                                 | –0.1                 |        | +V <sub>S</sub> – 0.7 | –0.1                 |        | +V <sub>S</sub> – 0.7 | V      |
|                                      | T <sub>A</sub> = –40°C                                 | –0.15                |        | +V <sub>S</sub> – 0.9 | –0.15                |        | +V <sub>S</sub> – 0.9 | V      |
|                                      | T <sub>A</sub> = +125°C                                | –0.05                |        | +V <sub>S</sub> – 0.6 | –0.05                |        | +V <sub>S</sub> – 0.6 | V      |
| Overvoltage Range                    | T <sub>A</sub> = –40°C to +125°C                       | +V <sub>S</sub> – 40 |        | –V <sub>S</sub> + 40  | +V <sub>S</sub> – 40 |        | –V <sub>S</sub> + 40  | V      |
| <b>OUTPUT</b>                        |  |                      |        |                       |                      |        |                       |        |
| Output Swing                         | T <sub>A</sub> = –40°C to +125°C                       |                      |        |                       |                      |        |                       |        |
| R <sub>L</sub> = 2 kΩ to 1.35 V      |  | 0.2                  |        | +V <sub>S</sub> – 0.2 | 0.2                  |        | +V <sub>S</sub> – 0.2 | V      |
| R <sub>L</sub> = 10 kΩ to 1.35 V     |  | 0.1                  |        | +V <sub>S</sub> – 0.1 | 0.1                  |        | +V <sub>S</sub> – 0.1 | V      |
| Short-Circuit Current                |  |                      | 13     |                       |                      | 13     |                       | mA     |
| <b>POWER SUPPLY</b>                  |  |                      |        |                       |                      |        |                       |        |
| Operating Range                      | Single-supply operation                                | 2.2                  |        | 36                    | 2.2                  |        | 36                    | V      |
| Quiescent Current                    | +V <sub>S</sub> = 2.7 V                                |                      |        |                       |                      |        |                       |        |
|                                      | T <sub>A</sub> = +25°C                                 |                      | 325    | 400                   |                      | 325    | 400                   | μA     |
|                                      | T <sub>A</sub> = –40°C                                 |                      | 250    | 325                   |                      | 250    | 325                   | μA     |
|                                      | T <sub>A</sub> = +85°C                                 |                      | 425    | 500                   |                      | 425    | 500                   | μA     |
|                                      | T <sub>A</sub> = +125°C                                |                      | 475    | 550                   |                      | 475    | 550                   | μA     |
| <b>TEMPERATURE RANGE</b>             |  |                      |        |                       |                      |        |                       |        |
|                                      |  | –40                  |        | +125                  | –40                  |        | +125                  | °C     |

<sup>1</sup> Input stage uses pnp transistors, so input bias current always flows into the part.

<sup>2</sup> At high gains, the part is bandwidth limited rather than slew rate limited.

<sup>3</sup> For G > 5, gain error specifications do not include the effects of External Resistor R<sub>G</sub>.

<sup>4</sup> Input voltage range of the AD8227 input stage. The input range depends on the common-mode voltage, differential voltage, gain, and reference voltage. See the Input Voltage Range section for more information.

## ABSOLUTE MAXIMUM RATINGS

Table 4.

| Parameter                         | Rating  |
|-----------------------------------|---|
| Supply Voltage                    | $\pm 18$ V                                      |
| Output Short-Circuit Current      | Indefinite                                      |
| Maximum Voltage at $-IN$ or $+IN$ | $-V_S + 40$ V                                   |
| Minimum Voltage at $-IN$ or $+IN$ | $+V_S - 40$ V                                   |
| REF Voltage                       | $\pm V_S$                                       |
| Storage Temperature Range         | $-65^{\circ}\text{C}$ to $+150^{\circ}\text{C}$ |
| Operating Temperature Range       | $-40^{\circ}\text{C}$ to $+125^{\circ}\text{C}$ |
| Maximum Junction Temperature      | $140^{\circ}\text{C}$                           |

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

## THERMAL RESISTANCE

$\theta_{JA}$  is specified for a device in free air.

Table 5.

| Package                          | $\theta_{JA}$ | Unit                        |
|----------------------------------|---------------|-----------------------------|
| 8-Lead MSOP, 4-Layer JEDEC Board | 135           | $^{\circ}\text{C}/\text{W}$ |
| 8-Lead SOIC, 4-Layer JEDEC Board | 121           | $^{\circ}\text{C}/\text{W}$ |

## ESD CAUTION



**ESD (electrostatic discharge) sensitive device.** Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

## PIN CONFIGURATION AND FUNCTION DESCRIPTIONS




Figure 2. Pin Configuration

07759-002

Table 6. Pin Function Descriptions

| Pin No. | Mnemonic         | Description  |
|---------|------------------|--|
| 1       | -IN              | Negative Input.  |
| 2, 3    | R <sub>G</sub>   | Gain Setting Pins. Place a gain resistor between these two pins. |
| 4       | +IN              | Positive Input.  |
| 5       | -V <sub>S</sub>  | Negative Supply.   |
| 6       | REF              | Reference. This pin must be driven by low impedance.             |
| 7       | V <sub>OUT</sub> | Output.  |
| 8       | +V <sub>S</sub>  | Positive Supply.   |



# TYPICAL PERFORMANCE CHARACTERISTICS

T = 25°C, V<sub>S</sub> = ±15 V, R<sub>L</sub> = 10 kΩ, unless otherwise noted.




Figure 3. Typical Distribution of Output Offset Voltage




Figure 6. Typical Distribution of Input Offset Voltage Drift, G = 100




Figure 4. Typical Distribution of Output Offset Voltage Drift




Figure 7. Typical Distribution of Input Bias Current




Figure 5. Typical Distribution of Input Offset Voltage




Figure 8. Typical Distribution of Input Offset Current




Figure 9. Input Common-Mode Voltage vs. Output Voltage, Single Supply,  $V_s = 2.7V$ ,  $G = 5$




Figure 12. Input Common-Mode Voltage vs. Output Voltage, Single Supply,  $V_s = 2.7V$ ,  $G = 100$




Figure 10. Input Common-Mode Voltage vs. Output Voltage, Single Supply,  $V_s = 5V$ ,  $G = 5$




Figure 13. Input Common-Mode Voltage vs. Output Voltage, Single Supply,  $V_s = 5V$ ,  $G = 100$




Figure 11. Input Common-Mode Voltage vs. Output Voltage, Dual Supply,  $V_s = \pm 5V$ ,  $G = 5$




Figure 14. Input Common-Mode Voltage vs. Output Voltage, Dual Supply,  $V_s = \pm 5V$ ,  $G = 100$




Figure 15. Input Common-Mode Voltage vs. Output Voltage, Dual Supply,  $V_S = \pm 15\text{ V}$ ,  $G = 5$




Figure 18. Input Overvoltage Performance,  $G = 5$ ,  $V_S = \pm 15\text{ V}$




Figure 16. Input Common-Mode Voltage vs. Output Voltage, Dual Supply,  $V_S = \pm 15\text{ V}$ ,  $G = 100$




Figure 19. Input Overvoltage Performance,  $G = 100$ ,  $V_S = 2.7\text{ V}$




Figure 17. Input Overvoltage Performance,  $G = 5$ ,  $V_S = 2.7\text{ V}$




Figure 20. Input Overvoltage Performance,  $G = 100$ ,  $V_S = \pm 15\text{ V}$




Figure 21. Input Bias Current vs. Common-Mode Voltage,  $V_s = 5\text{ V}$




Figure 24. Negative PSRR vs. Frequency




Figure 22. Input Bias Current vs. Common-Mode Voltage,  $V_s = \pm 15\text{ V}$




Figure 25. Gain vs. Frequency,  $V_s = \pm 15\text{ V}$




Figure 23. Positive PSRR vs. Frequency, RTI




Figure 26. Gain vs. Frequency,  $V_s = 2.7\text{ V}$




Figure 27. CMRR vs. Frequency, RTI

07759-027




Figure 30. Input Bias Current and Offset Current vs. Temperature

07759-030




Figure 28. CMRR vs. Frequency, RTI, 1 kΩ Source Imbalance

07759-028




Figure 31. Gain Error vs. Temperature, G = 5

07759-031




Figure 29. Change in Input Offset Voltage vs. Warm-Up Time

07759-029




Figure 32. CMRR vs. Temperature, G = 5

07759-032




Figure 33. Input Voltage Limit vs. Supply Voltage




Figure 36. Output Voltage Swing vs. Load Resistance




Figure 34. Output Voltage Swing vs. Supply Voltage,  $R_L = 10\text{ k}\Omega$




Figure 37. Output Voltage Swing vs. Output Current




Figure 35. Output Voltage Swing vs. Supply Voltage,  $R_L = 2\text{ k}\Omega$




Figure 38. Gain Nonlinearity,  $G = 5$ ,  $R_L \geq 2\text{ k}\Omega$




Figure 39. Gain Nonlinearity,  $G = 10$ ,  $R_L \geq 2 \text{ k}\Omega$

07759-039




Figure 42. Voltage Noise Spectral Density vs. Frequency

07759-042




Figure 40. Gain Nonlinearity,  $G = 100$ ,  $R_L \geq 2 \text{ k}\Omega$

07759-040




Figure 43. 0.1 Hz to 10 Hz RTI Voltage Noise,  $G = 5$ ,  $G = 1000$

07759-043




Figure 41. Gain Nonlinearity,  $G = 1000$ ,  $R_L \geq 2 \text{ k}\Omega$

07759-041




Figure 44. Current Noise Spectral Density vs. Frequency

07759-044




Figure 45. 0.1 Hz to 10 Hz Current Noise




Figure 48. Large-Signal Pulse Response and Settling Time,  $G = 10$ , 10 V Step,  $V_s = \pm 15$  V




Figure 46. Large-Signal Frequency Response




Figure 49. Large-Signal Pulse Response and Settling Time,  $G = 100$ , 10 V Step,  $V_s = \pm 15$  V




Figure 47. Large-Signal Pulse Response and Settling Time,  $G = 5$ , 10 V Step,  $V_s = \pm 15$  V




Figure 50. Large-Signal Pulse Response and Settling Time,  $G = 1000$ , 10 V Step,  $V_s = \pm 15$  V






Figure 51. Small-Signal Pulse Response,  $G = 5$ ,  $R_L = 10\text{ k}\Omega$ ,  $C_L = 100\text{ pF}$




Figure 53. Small-Signal Pulse Response,  $G = 100$ ,  $R_L = 10\text{ k}\Omega$ ,  $C_L = 100\text{ pF}$




Figure 52. Small-Signal Pulse Response,  $G = 10$ ,  $R_L = 10\text{ k}\Omega$ ,  $C_L = 100\text{ pF}$




Figure 54. Small-Signal Pulse Response,  $G = 1000$ ,  $R_L = 10\text{ k}\Omega$ ,  $C_L = 100\text{ pF}$




Figure 55. Small-Signal Pulse Response with Various Capacitive Loads,  $G = 5$ ,  $R_L = \text{Infinity}$




Figure 57. Supply Current vs. Supply Voltage




Figure 56. Settling Time vs. Step Size,  $V_s = \pm 15\text{ V}$ , Dual Supply

## THEORY OF OPERATION




Figure 58. Simplified Schematic

### ARCHITECTURE

The AD8227 is based on the classic three op amp topology. This topology has two stages: a preamplifier to provide differential amplification followed by a difference amplifier that removes the common-mode voltage and provides additional amplification. Figure 58 shows a simplified schematic of the AD8227.

The first stage works as follows. To maintain a constant voltage across the bias resistor,  $R_B$ , Amplifier A1 must keep Node 3 at a constant diode drop above the positive input voltage. Similarly, Amplifier A2 keeps Node 4 at a constant diode drop above the negative input voltage. Therefore, a replica of the differential input voltage is placed across the gain setting resistor,  $R_G$ . The current that flows across this resistance must also flow through the  $R1$  and  $R2$  resistors, creating a gained differential signal between the A2 and A1 outputs. Note that, in addition to a gained differential signal, the original common-mode signal, shifted a diode drop up, is also still present.

The second stage is a difference amplifier, composed of Amplifier A3 and the  $R3$  through  $R6$  resistors. This stage removes the common-mode signal from the amplified differential signal and gains it by 5.

The transfer function of the AD8227 is

$$V_{OUT} = G \times (V_{IN+} - V_{IN-}) + V_{REF}$$

where:

$$G = 5 + \frac{80 \text{ k}\Omega}{R_G}$$

### GAIN SELECTION

Placing a resistor across the  $R_G$  terminals sets the gain of the AD8227. The gain can be calculated by referring to Table 7 or by using the following gain equation:

$$R_G = \frac{80 \text{ k}\Omega}{G - 5}$$

Table 7. Gains Achieved Using Common Resistor Values

| Standard Table Value of $R_G$ | Calculated Gain |
|-------------------------------|-----------------|
| No resistor                   | 5               |
| 100 kΩ                        | 5.8             |
| 49.9 kΩ                       | 6.6             |
| 26.7 kΩ                       | 8               |
| 20 kΩ                         | 9               |
| 16 kΩ                         | 10              |
| 10 kΩ                         | 13              |
| 5.36 kΩ                       | 19.9            |
| 2 kΩ                          | 45              |
| 1.78 kΩ                       | 49.9            |
| 1 kΩ                          | 85              |
| 845 Ω                         | 99.7            |
| 412 Ω                         | 199             |
| 162 Ω                         | 499             |
| 80.6 Ω                        | 998             |

The AD8227 defaults to  $G = 5$  when no gain resistor is used. The tolerance and gain drift of the  $R_G$  resistor should be added to the specifications of the AD8227 to determine the total gain accuracy of the system. When the gain resistor is not used, gain error and gain drift are minimal.

## REFERENCE TERMINAL

The output voltage of the AD8227 is developed with respect to the potential on the reference terminal. This is useful when the output signal needs to be offset to a precise midsupply level. For example, a voltage source can be tied to the REF pin to level-shift the output so that the AD8227 can drive a single-supply ADC. The REF pin is protected with ESD diodes and should not exceed either  $+V_S$  or  $-V_S$  by more than 0.3 V.

For best performance, source impedance to the REF terminal should be kept below  $2\ \Omega$ . As shown in Figure 58, the reference terminal, REF, is at one end of a  $50\ \text{k}\Omega$  resistor. Additional impedance at the REF terminal adds to this  $50\ \text{k}\Omega$  resistor and results in amplification of the signal connected to the positive input. The amplification from the additional  $R_{REF}$  can be calculated as follows:

$$6(50\ \text{k}\Omega + R_{REF}) / (60\ \text{k}\Omega + R_{REF})$$

Only the positive signal path is amplified; the negative path is unaffected. This uneven amplification degrades CMRR.




Figure 59. Driving the Reference Pin

## INPUT VOLTAGE RANGE

Most instrumentation amplifiers have a very limited output voltage swing when the common-mode voltage is near the upper or lower limit of the part's input range. The AD8227 has very little of this limitation. See Figure 9 through Figure 16 for the input common-mode range vs. output voltage of the part.

## LAYOUT

To ensure optimum performance of the AD8227 at the PCB level, care must be taken in the design of the board layout. The pins of the AD8227 are arranged in a logical manner to aid in this task.




Figure 60. Pinout Diagram

## Common-Mode Rejection Ratio over Frequency

Poor layout can cause some of the common-mode signals to be converted to differential signals before reaching the in-amp. Such conversions occur when one input path has a frequency response that is different from the other. To keep CMRR over frequency high, the input source impedance and capacitance of each path should be closely matched. Additional source resistance in the input path (for example, for input protection) should be placed close to the in-amp inputs, which minimizes the interaction of the source resistance with parasitic capacitance from the PCB traces.

Parasitic capacitance at the gain setting pins can also affect CMRR over frequency. If the board design has a component at the gain setting pins (for example, a switch or jumper), the component should be chosen so that the parasitic capacitance is as small as possible.

## Power Supplies

A stable dc voltage should be used to power the instrumentation amplifier. Noise on the supply pins can adversely affect performance. See the PSRR performance curves in Figure 23 and Figure 24 for more information.

A  $0.1\ \mu\text{F}$  capacitor should be placed as close as possible to each supply pin. As shown in Figure 61, a  $10\ \mu\text{F}$  tantalum capacitor can be used farther away from the part. In most cases, it can be shared by other precision integrated circuits.




Figure 61. Supply Decoupling, REF, and Output Referred to Local Ground

## References

The output voltage of the AD8227 is developed with respect to the potential on the reference terminal. Care should be taken to tie REF to the appropriate local ground.

## INPUT BIAS CURRENT RETURN PATH

The input bias current of the AD8227 must have a return path to ground. When the source, such as a thermocouple, cannot provide a return current path, one should be created, as shown in Figure 62.




Figure 62. Creating an Input Bias Current Return Path

## INPUT PROTECTION

The AD8227 has very robust inputs and typically does not need additional input protection. Input voltages can be up to 40 V from the opposite supply rail. For example, with a +5 V positive supply and a -8 V negative supply, the part can safely withstand voltages from -35 V to +32 V. Unlike some other instrumentation amplifiers, the part can handle large differential input voltages even when the part is in high gain. Figure 17 through Figure 20 show the behavior of the part under overvoltage conditions.

The other AD8227 terminals should be kept within the supplies. All terminals of the AD8227 are protected against ESD.

For applications where the AD8227 encounters voltages beyond the allowed limits, external current limiting resistors and low leakage diode clamps such as the BAV199L, the FJH1100s, or the SP720 should be used.

## RADIO FREQUENCY INTERFERENCE (RFI)

RF rectification is often a problem when amplifiers are used in applications that have strong RF signals. The disturbance can appear as a small dc offset voltage. High frequency signals can be filtered with a low-pass RC network placed at the input of the instrumentation amplifier, as shown in Figure 63. The filter limits the input signal bandwidth, according to the following relationship:

$$FilterFrequency_{DIFF} = \frac{1}{2\pi R(2C_D + C_C)}$$

$$FilterFrequency_{CM} = \frac{1}{2\pi RC_C}$$

where  $C_D \geq 10 C_C$ .




Figure 63. RFI Suppression

$C_D$  affects the differential signal and  $C_C$  affects the common-mode signal. Values of  $R$  and  $C_C$  should be chosen to minimize RFI. A mismatch between  $R \times C_C$  at the positive input and  $R \times C_C$  at the negative input degrades the CMRR of the AD8227. By using a value of  $C_D$  one magnitude larger than  $C_C$ , the effect of the mismatch is reduced, and performance is improved.

## APPLICATIONS INFORMATION

### DIFFERENTIAL DRIVE

Figure 64 shows how to configure the AD8227 for differential output.




Figure 64. Differential Output Using an Op Amp

The differential output is set by the following equation:

$$V_{DIFF\_OUT} = V_{OUT+} - V_{OUT-} = Gain \times (V_{IN+} - V_{IN-})$$

The common-mode output is set by the following equation:

$$V_{CM\_OUT} = (V_{OUT+} + V_{OUT-})/2 = V_{BIAS}$$

The advantage of this circuit is that the dc differential accuracy depends on the AD8227 and not on the op amp or the resistors. This circuit takes advantage of the AD8227's precise control of its output voltage relative to the reference voltage. Op amp dc performance and resistor matching affect the dc common-mode output accuracy. However, because common-mode errors are likely to be rejected by the next device in the signal chain, these errors typically have little effect on overall system accuracy.

### Tips for Best Differential Output Performance

For best ac performance, an op amp with at least 2 MHz gain bandwidth and 1 V/μs slew rate is recommended. Good choices for op amps are the AD8641, AD8515, or AD820.

Keep trace lengths from resistors to the inverting terminal of the op amp as short as possible. Excessive capacitance at this node can cause the circuit to be unstable. If capacitance cannot be avoided, use lower value resistors.

### PRECISION STRAIN GAGE

The low offset and high CMRR over frequency of the AD8227 make it an excellent choice for bridge measurements. The bridge can be connected directly to the inputs of the amplifier (see Figure 65).




Figure 65. Precision Strain Gage

## DRIVING AN ADC

Figure 66 shows several different methods for driving an ADC. The ADC in the [ADuC7026](#) microcontroller was chosen for this example because it has an unbuffered charge sampling architecture that is typical of most modern ADCs. This type of architecture typically requires an RC buffer stage between the ADC and the amplifier to work correctly.

Option 1 shows the minimum configuration required to drive a charge sampling ADC. The capacitor provides charge to the ADC sampling capacitor, and the resistor shields the AD8227 from the capacitance. To keep the AD8227 stable, the RC time constant of the resistor and capacitor needs to stay above 5  $\mu$ s. This circuit is mainly useful for lower frequency signals.

Option 2 shows a circuit for driving higher frequency signals. It uses a precision op amp ([AD8616](#)) with relatively high bandwidth and output drive. This amplifier can drive a resistor and capacitor with a much higher time constant and is, therefore, suited for higher frequency applications.

Option 3 is useful for applications where the AD8227 needs to run off a large voltage supply but drives a single-supply ADC. In normal operation, the AD8227 output stays within the ADC range, and the AD8616 simply buffers it. However, in a fault condition, the output of the AD8227 may go outside the supply range of both the AD8616 and the ADC. This is not an issue in the circuit, because the 10 k $\Omega$  resistor between the two amplifiers limits the current into the AD8616 to a safe level.






Figure 66. Driving an ADC

## OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MO-187-AA

Figure 67. 8-Lead Mini Small Outline Package [MSOP] (RM-8)  
Dimensions shown in millimeters



COMPLIANT TO JEDEC STANDARDS MS-012-AA  
CONTROLLING DIMENSIONS ARE IN MILLIMETERS; INCH DIMENSIONS (IN PARENTHESES) ARE ROUNDED-OFF MILLIMETER EQUIVALENTS FOR REFERENCE ONLY AND ARE NOT APPROPRIATE FOR USE IN DESIGN.

Figure 68. 8-Lead Standard Small Outline Package [SOIC\_N] Narrow Body (R-8)  
Dimensions shown in millimeters and (inches)

## ORDERING GUIDE

| Model                      | Temperature Range | Package Description              | Package Option | Branding |
|----------------------------|-------------------|----------------------------------|----------------|----------|
| AD8227ARMZ <sup>1</sup>    | -40°C to +125°C   | 8-Lead MSOP                      | RM-8           | Y1S      |
| AD8227ARMZ-RL <sup>1</sup> | -40°C to +125°C   | 8-Lead MSOP, 13" Tape and Reel   | RM-8           | Y1S      |
| AD8227ARMZ-R7 <sup>1</sup> | -40°C to +125°C   | 8-Lead MSOP, 7" Tape and Reel    | RM-8           | Y1S      |
| AD8227ARZ <sup>1</sup>     | -40°C to +125°C   | 8-Lead SOIC_N                    | R-8            |          |
| AD8227ARZ-RL <sup>1</sup>  | -40°C to +125°C   | 8-Lead SOIC_N, 13" Tape and Reel | R-8            |          |
| AD8227ARZ-R7 <sup>1</sup>  | -40°C to +125°C   | 8-Lead SOIC_N, 7" Tape and Reel  | R-8            |          |
| AD8227BRMZ <sup>1</sup>    | -40°C to +125°C   | 8-Lead MSOP                      | RM-8           | Y1U      |
| AD8227BRMZ-RL <sup>1</sup> | -40°C to +125°C   | 8-Lead MSOP, 13" Tape and Reel   | RM-8           | Y1U      |
| AD8227BRMZ-R7 <sup>1</sup> | -40°C to +125°C   | 8-Lead MSOP, 7" Tape and Reel    | RM-8           | Y1U      |
| AD8227BRZ <sup>1</sup>     | -40°C to +125°C   | 8-Lead SOIC_N                    | R-8            |          |
| AD8227BRZ-RL <sup>1</sup>  | -40°C to +125°C   | 8-Lead SOIC_N, 13" Tape and Reel | R-8            |          |
| AD8227BRZ-R7 <sup>1</sup>  | -40°C to +125°C   | 8-Lead SOIC_N, 7" Tape and Reel  | R-8            |          |

<sup>1</sup> Z = RoHS Compliant Part.