



**ELECTRONICS, INC.**  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089

## NTE1818 Integrated Circuit Module, AF PO, 25W/Ch, Dual Power Supply

**Features:**

- Muting circuit to cut off pop noise
- Greatly reduced heat sink due to case temperature +125°C guaranteed

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Maximum Supply Voltage, $V_{CC\ max}$	±39V
Thermal Resistance, Junction-to-Case, $R_{thJC}$	2.6°C/W
Junction Temperature, $T_J$	150°C
Operating Case Temperature, $T_C$	125°C
Storage Temperature Range, $T_{stg}$	-30° to +125°C
Available Time for Load Shorted ( $V_{CC} = \pm 26V, R_L = 8\Omega, f = 50Hz, P_O = 25W$ ), $t_s$	2sec

**Recommended Operating Conditions:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Recommended Operating Voltage, $V_{CC}$	±26V
Load Resistance, $R_L$	8Ω

**Operating Characteristics:** ( $T_A = +25^\circ\text{C}, V_{CC} = \pm 26V, R_L = 8\Omega, R_g = 600\Omega, VG = 40dB$ ,  
 $R_L$ : non-inductive load, unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Quiescent Current	$I_{CCO}$	$V_{CC} = \pm 31V$	20	40	100	mA
Output Power	$P_{O(1)}$	THD – 0.4%, $f = 20Hz \sim 20kHz$	25	–	–	W
	$P_{O(2)}$	$V_{CC} = \pm 22V, THD = 1.0\%$	25	–	–	W
Total Harmonic Distortion	THD	$P_O = 1.0W, f = 1kHz$	–	–	0.3	%
Frequency Response	$f_L, f_H$	$P_O = 1.0W, -3dB$	20 to 50k			Hz
Input Resistance	$r_i$	$P_O = 1.0W, f = 1kHz$	–	55	–	kΩ
Output Noise Voltage	$V_{NO}$	$V_{CC} = \pm 31V, R_g = 10k\Omega$	–	–	1.2	mV <sub>rms</sub>
Midpoint Voltage	$V_N$	$V_{CC} = \pm 31V$	-70	0	70	mV
Muting Voltage	$V_M$		-2	-5	-10	V

### Pin Connection Diagram

<b>18</b>	Rt Ch Input (-)
<b>17</b>	Rt Ch Input (+)
<b>16</b>	GND
<b>15</b>	Compensation
<b>14</b>	(-) V <sub>CC</sub>
<b>13</b>	Rt Ch Output
<b>12</b>	Bypass
<b>11</b>	(+) V <sub>CC</sub>
<b>10</b>	Lt Ch Output
<b>9</b>	(-) V <sub>CC</sub>
<b>8</b>	Compensation
<b>7</b>	Compensation
<b>6</b>	Muting
<b>5</b>	Compensation
<b>4</b>	Compensation
<b>3</b>	Compensation
<b>2</b>	Lt Ch Input (+)
<b>1</b>	Lt Ch Input (-)

