

SANYO

No.1942A

2SA1391/2SC3382

PNP/NPN Epitaxial Planar Silicon Transistors

Low-Noise AF Amp Applications

Features

- . Adoption of FBET process
- . AF amp
- . Low-noise use

(): 2SA1391

Absolute Maximum Ratings at Ta=25°C

			unit
Collector to Base Voltage	V_{CB0}	(-)60	V
Collector to Emitter Voltage	V_{CE0}	(-)50	V
Emitter to Base Voltage	V_{EBO}	(-)6	V
Collector Current	I_C	(-)200	mA
Collector Current(Pulse)	I_{CP}	(-)400	mA
Collector Dissipation	P_C	400	mW
Junction Temperature	T_J	150	°C
Storage Temperature	T_{stg}	-55 to +150	°C


Electrical Characteristics at Ta=25°C

			min	typ	max	unit
Collector Cutoff Current	I_{CBO}	$V_{CB}=(-)40V, I_E=0$		(-)0.1		μA
Emitter Cutoff Current	I_{EBO}	$V_{EB}=(-)5V, I_C=0$		(-)0.1		μA
DC Current Gain	$h_{FE}(1)$	$V_{CE}=(-)6V, I_C=(-)1mA$	100*		560*	
	$h_{FE}(2)$	$V_{CE}=(-)6V, I_C=(-)0.1mA$	70			
Gain-Bandwidth Product	f_T	$V_{CE}=(-)6V, I_C=(-)10mA$		250		MHz
				(200)		MHz
C-E Saturation Voltage	$V_{CE(sat)}$	$I_C=(-)100mA, I_B=(-)10mA$		(-)0.3		V
B-E Saturation Voltage	$V_{BE(sat)}$	$I_C=(-)100mA, I_B=(-)10mA$		(-)1.0		V
Output Capacitance	c_{ob}	$V_{CB}=(-)6V, f=1MHz$		2.7		pF
				(3.7)		pF
C-B Breakdown Voltage	$V_{(BR)CBO}$	$I_C=10\mu A, I_E=0$		(-)60		V
C-E Breakdown Voltage	$V_{(BR)CEO}$	$I_C=(-)1mA, R_{BE}=\infty$		(-)50		V
E-B Breakdown Voltage	$V_{(BR)EBO}$	$I_E=(-)10\mu A, I_C=0$		(-)6		V
Noise Level	$V_{NO(ave)}$	$V_{CC}=(-)30V, I_C=(-)1mA, R_g=56k\Omega, V_G=77dB/1kHz$			40	mV
					(35)	mV
Noise Peak Level	$V_{NO(peak)}$	$V_{CC}=(-)30V, I_C=(-)1mA, R_g=56k\Omega, V_G=77dB/1kHz$			280	mV
					(200)	mV


*: The 2SA1391/2SC3382 are classified by 1mA h_{FE} as follows:









100	R	200	140	S	280	200	T	400	280	U	560
-----	---	-----	-----	---	-----	-----	---	-----	-----	---	-----









Noise Test Circuit













Package Dimensions 2003A
(unit: mm)











- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use.
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.