

TLE207x-Q1, TLE207xA-Q1 EXCALIBUR LOW-NOISE HIGH-SPEED JFET-INPUT OPERATIONAL AMPLIFIERS

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

- Qualification in Accordance With AEC-Q100†
- Qualified for Automotive Applications
- Customer-Specific Configuration Control Can Be Supported Along With Major-Change Approval
- Direct Upgrades to TL05x, TL07x, and TL08x BiFET Operational Amplifiers
- Greater Than $2\times$ Bandwidth (10 MHz) and $3\times$ Slew Rate (45 V/ μ s) Than TL07x
- Ensured Maximum Noise Floor 17 nV/ $\sqrt{\text{Hz}}$
- On-Chip Offset Voltage Trimming for Improved DC Performance
- Wider Supply Rails Increase Dynamic Signal Range to ± 19 V

† Contact Texas Instruments for details. Q100 qualification data available on request.

description/ordering information

The TLE207x series of JFET-input operational amplifiers more than double the bandwidth and triple the slew rate of the TL07x and TL08x families of BiFET operational amplifiers. Texas Instruments Excalibur process yields a typical noise floor of 11.6 nV/ $\sqrt{\text{Hz}}$, 17-nV/ $\sqrt{\text{Hz}}$ ensured maximum, offering immediate improvement in noise-sensitive circuits designed using the TL07x. The TLE207x also has wider supply voltage rails, increasing the dynamic signal range for BiFET circuits to ± 19 V. On-chip zener trimming of offset voltage yields precision grades for greater accuracy in dc-coupled applications. The TLE207x are pin-compatible with lower performance BiFET operational amplifiers for ease in improving performance in existing designs.

BiFET operational amplifiers offer the inherently higher input impedance of the JFET-input transistors, without sacrificing the output drive associated with bipolar amplifiers. This makes them better suited for interfacing with high-impedance sensors or very low-level ac signals. They also feature inherently better ac response than bipolar or CMOS devices having comparable power consumption.

The TLE207x family of BiFET amplifiers are Texas Instruments highest performance BiFETs, with tighter input offset voltage and ensured maximum noise specifications. Designers requiring less stringent specifications but seeking the improved ac characteristics of the TLE207x should consider the TLE208x operational amplifier family.

Because BiFET operational amplifiers are designed for use with dual power supplies, care must be taken to observe common-mode input voltage limits and output swing when operating from a single supply. DC biasing of the input signal is required and loads should be terminated to a virtual ground node at mid-supply. Texas Instruments TLE2426 integrated virtual ground generator is useful when operating BiFET amplifiers from single supplies.

ORDERING INFORMATION

TA	$V_{IO\text{max}}$ AT 25°C	PACKAGE†		ORDERABLE PART NUMBER	TOP-SIDE MARKING
–40°C to 125°C	2 mV	SOIC – D	Tape and reel	TLE2071AQDRQ1	2071AQ
	4 mV	SOIC – D	Tape and reel	TLE2071QDRQ1	2071Q1
	3.5 mV	SOIC – D	Tape and reel	TLE2072AQDRQ1	2072AQ
	6 mV	SOIC – D	Tape and reel	TLE2072QDRQ1	2072Q1
	4 mV	SOP – DW	Tape and reel	TLE2074AQDWRQ1‡	TLE2074AQ1
	7 mV	SOP – DW	Tape and reel	TLE2074QDWRQ1‡	TLE2074Q1

† Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at www.ti.com/sc/package.

‡ Product Preview



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2004, Texas Instruments Incorporated



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**


SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

description/ordering information (continued)

The TLE207x are fully specified at ± 15 V and ± 5 V. For operation in low-voltage and/or single-supply systems, Texas Instruments LinCMOS families of operational amplifiers (TLC- and TLV-prefix) are recommended. When moving from BiFET to CMOS amplifiers, particular attention should be paid to slew rate and bandwidth requirements and output loading.


TLE2071 AND TLE2071A

**D PACKAGE
(TOP VIEW)**




TLE2072 AND TLE2072A

**D PACKAGE
(TOP VIEW)**




TLE2074 AND TLE2074A

**DW PACKAGE
(TOP VIEW)**



NC – No internal connection


symbol



**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SLOS181A – FEBRUARY 1997 – REVISED MARCH 2000 (sourced from

equivalent schematic



NOTES: A. OFFSET N1 AND OFFSET N2 are only available on the TLE2071x devices.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SLOS181A – FEBRUARY 1997 – REVISED MARCH 2000 (sourced from)

COMPONENT	ACTUAL DEVICE COMPONENT COUNT		
	TLE2071	TLE2072	TLE2074
Transistors	33	57	114
Resistors	25	37	74
Diodes	8	5	10
Capacitors	6	11	22

equivalent schematic (continued)



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage, V_{CC+} (see Note 1)	19 V
Supply voltage, V_{CC-} (see Note 1)	-19 V
Differential input voltage range, V_{ID} (see Note 2)	V_{CC+} to V_{CC-}
Input voltage range, V_I (any input)	V_{CC+} to V_{CC-}
Input current, I_I (each input)	±1 mA
Output current, I_O (each output)	±80 mA
Total current into V_{CC+}	160 mA
Total current out of V_{CC-}	160 mA
Duration of short-circuit current at (or below) 25°C (see Note 3)	unlimited
Maximum Junction Temperature, T_J	150°C
Package thermal impedance, θ_{JA} (see Note 4):D package	126°C/W
DW package	75°C/W
Operating free-air temperature range, T_A : Q suffix	-40°C to 125°C
Storage temperature range	-65°C to 150°C
Lead temperature 1,6 mm (1/16 inch) from case for 3 seconds	300°C

† Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- NOTES:
1. All voltage values, except differential voltages, are with respect to the midpoint between V_{CC+} and V_{CC-} .
 2. Differential voltages are at the noninverting input with respect to the inverting input.
 3. The output may be shorted to either supply. Temperatures and/or supply voltages must be limited to ensure that the maximum dissipation rate is not exceeded.
 4. The package thermal impedance is calculated in accordance with JESD 51-7.

recommended operating conditions

		MIN	MAX	UNIT
Supply voltage, $V_{CC\pm}$		±2.25	±19	V
Common-mode input voltage, V_{IC}	$V_{CC\pm} = \pm 5$ V	-0.8	5	V
	$V_{CC\pm} = \pm 15$ V	-10.8	15	
Operating free-air temperature, T_A		-40	125	°C

TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2071-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2071-Q1			TLE2071A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{IO}	Input offset voltage $V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$,	25°C	0.34	4	9	0.3	2	7	mV
αV_{IO}		Full range							
I_{IO}	Input offset current $V_{IC} = 0$, $V_O = 0$, See Figure 4	25°C	5	100	20	5	100	20	pA
I_{IB}		Full range							nA
I_{IB}		25°C	15	175	60	15	175	60	pA
I_{IB}		Full range							nA
V_{ICR}	Common-mode input voltage range $R_S = 50 \Omega$	25°C	5 to -1	5 to -1.9	5 to -1.9	5 to -1	5 to -1.9	5 to -1.9	V
V_{ICR}		Full range	5 to -0.8		5 to -0.8		5 to -0.8		
V_{OM+}	$I_O = -200 \mu A$	25°C	3.8	4.1	3.8	4.1			V
		Full range	3.6		3.6				
	$I_O = -2 mA$	25°C	3.5	3.9	3.5	3.9			
		Full range	3.3		3.3				
	$I_O = -20 mA$	25°C	1.5	2.3	1.5	2.3			
		Full range	1.4		1.4				
	$I_O = 200 \mu A$	25°C	-3.8	-4.2	-3.8	-4.2			V
		Full range	-3.6		-3.6				
V_{OM-}	$I_O = 2 mA$	25°C	-3.5	-4.1	-3.5	-4.1			
		Full range	-3.3		-3.3				
	$I_O = 20 mA$	25°C	-1.5	-2.4	-1.5	-2.4			
		Full range	-1.4		-1.4				
	$V_O = \pm 2.3 V$	$R_L = 600 \Omega$	25°C	80	91	80	91		dB
			Full range	78		78			
	$V_O = \pm 2.3 V$	$R_L = 2 k\Omega$	25°C	90	100	90	100		
			Full range	88		88			
	$V_O = \pm 2.3 V$	$R_L = 10 k\Omega$	25°C	95	106	95	106		
			Full range	93		93			
r_i	Input resistance	$V_{IC} = 0$	25°C	10^{12}		10^{12}		Ω	
c_i	Input capacitance See Figure 5	Common mode	25°C	11		11			pF
c_i			25°C	2.5		2.5			
Z_o	Open-loop output impedance	$f = 1 MHz$	25°C	80		80		Ω	
CMRR	Common-mode rejection ratio	$V_{IC} = V_{ICR\min}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	70	89	70	89		dB
			Full range	68		68			
k _{SVR}	Supply-voltage rejection ratio ($\Delta V_{CC\pm} / \Delta V_{IO}$)	$V_{CC\pm} = \pm 5 V$ to $\pm 15 V$, $V_O = 0$, $R_S = 50 \Omega$	25°C	82	99	82	99		dB
			Full range	80		80			

[†] Full range is $-40^\circ C$ to $125^\circ C$.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLE207x-Q1, TLE207xA-Q1
**EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2071-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V (unless otherwise noted) (continued)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2071-Q1			TLE2071A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
I_{CC} Supply current	$V_O = 0$, No load	25°C	1.35	1.6	2.2	1.35	1.6	2.2	mA
		Full range			2.2			2.2	
I_{OS} Short-circuit output current	$V_O = 0$	$V_{ID} = 1$ V			-35			-35	mA
		$V_{ID} = -1$ V			45			45	

† Full range is -40°C to 125°C .

TLE2071-Q1 operating characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2071-Q1			TLE2071A-Q1			UNIT	
			MIN	TYP	MAX	MIN	TYP	MAX		
SR+ Positive slew rate	$V_O(\text{PP}) = \pm 2.3$ V, $\text{AVD} = -1$, $R_L = 2$ k Ω , $C_L = 100$ pF, See Figure 1	25°C		35			35		V/ μ s	
		Full range	20			20				
SR- Negative slew rate		25°C		38			38		V/ μ s	
		Full range	20			20				
t_s Settling time	$\text{AVD} = -1$, 2-V step, $R_L = 1$ k Ω , $C_L = 100$ pF	To 10 mV	25°C		0.25		0.25		μ s	
		To 1 mV			0.4		0.4			
V_n Equivalent input noise voltage	$f = 10$ Hz $f = 10$ kHz	25°C	28	55		28	55		nV/ $\sqrt{\text{Hz}}$	
			11.6	17		11.6	17			
$V_{N(\text{PP})}$ Peak-to-peak equivalent input noise voltage	$R_S = 20$ Ω , See Figure 3	$f = 10$ Hz to 10 kHz	25°C		6		6		μ V	
					0.6		0.6			
I_n Equivalent input noise current	$V_{IC} = 0$,	$f = 10$ kHz	25°C		2.8		2.8		fA/ $\sqrt{\text{Hz}}$	
THD + N Total harmonic distortion plus noise	$V_O(\text{PP}) = 5$ V, $f = 1$ kHz, $R_S = 25$ Ω	$\text{AVD} = 10$, $R_L = 2$ k Ω ,	25°C		0.013%		0.013%			
B_1 Unity-gain bandwidth	$V_I = 10$ mV, $C_L = 25$ pF,	$R_L = 2$ k Ω , See Figure 2	25°C		9.4		9.4		MHz	
B_{OM} Maximum output-swing bandwidth	$V_O(\text{PP}) = 4$ V, $R_L = 2$ k Ω ,	$\text{AVD} = -1$, $C_L = 25$ pF	25°C		2.8		2.8		MHz	
ϕ_m Phase margin at unity gain	$V_I = 10$ mV, $C_L = 25$ pF,	$R_L = 2$ k Ω , See Figure 2	25°C		56		56			

† Full range is -40°C to 125°C .

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2071-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2071-Q1			TLE2071A-Q1			UNIT	
			MIN	TYP	MAX	MIN	TYP	MAX		
V_{IO} Input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$	25°C	0.49	4	9	0.47	2	7	mV	
		Full range								
α_{VIO} Temperature coefficient of input offset voltage		Full range		3.2			3.2	20	$\mu\text{V}/^\circ\text{C}$	
I_{IO} Input offset current	$V_{IC} = 0$, $V_O = 0$, See Figure 4	25°C	6	100	20	6	100	20	pA	
		Full range								
I_{IB} Input bias current		25°C	20	175	60	20	175	60		
		Full range								
V_{ICR} Common-mode input voltage range	$R_S = 50 \Omega$	25°C	15 to -11	15 to -11.9	15 to -11.9	15 to -11	15 to -11.9	15 to -11.9	V	
		Full range								
V_{OM+} Maximum positive peak output voltage swing	$I_O = -200 \mu\text{A}$	25°C	13.8	14.1	13.8	14.1			V	
		Full range	13.6		13.6					
	$I_O = -2 \text{ mA}$	25°C	13.5	13.9	13.5	13.9				
		Full range	13.3		13.3					
	$I_O = -20 \text{ mA}$	25°C	11.5	12.3	11.5	12.3				
		Full range	11.4		11.4					
V_{OM-} Maximum negative peak output voltage swing	$I_O = 200 \mu\text{A}$	25°C	-13.8	-14.2	-13.8	-14.2			V	
		Full range	-13.6		-13.6					
	$I_O = 2 \text{ mA}$	25°C	-13.5	-14	-13.5	-14				
		Full range	-13.3		-13.3					
	$I_O = 20 \text{ mA}$	25°C	-11.5	-12.4	-11.5	-12.4				
		Full range	-11.4		-11.4					
A_{VD} Large-signal differential voltage amplification	$V_O = \pm 10 \text{ V}$	$R_L = 600 \Omega$	25°C	80	96	80	96		dB	
			Full range	78		78				
		$R_L = 2 \text{ k}\Omega$	25°C	90	109	90	109			
			Full range	88		88				
		$R_L = 10 \text{ k}\Omega$	25°C	95	118	95	118			
			Full range	93		93				
r_i Input resistance	$V_{IC} = 0$	25°C		1012		1012			Ω	
c_i Input capacitance	$V_{IC} = 0$, See Figure 5	Common mode	25°C		7.5		7.5		pF	
		Differential	25°C		2.5		2.5			
z_o Open-loop output impedance	$f = 1 \text{ MHz}$	25°C		80		80			Ω	
CMRR Common-mode rejection ratio	$V_{IC} = V_{ICR\min}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	80	98	80	98			dB	
		Full range	78		78					
k_{SVR} Supply-voltage rejection ratio ($\Delta V_{CC\pm}/\Delta V_{IO}$)	$V_{CC\pm} = \pm 5 \text{ V to } \pm 15 \text{ V}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	82	99	82	99			dB	
		Full range	80		80					

[†] Full range is -40°C to 125°C .



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLE207x-Q1, TLE207xA-Q1
**EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2071-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V (unless otherwise noted) (continued)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2071-Q1			TLE2071A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
I_{CC} Supply current	$V_O = 0$, No load	25°C	1.35	1.7	2.2	1.35	1.7	2.2	mA
		Full range			2.2			2.2	
I_{OS} Short-circuit output current	$V_O = 0$	$V_{ID} = 1$ V	25°C	-30	-45	-30	-45		mA
		$V_{ID} = -1$ V		30	48	30	48		

† Full range is -40°C to 125°C.

TLE2071-Q1 operating characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2071-Q1			TLE2071A-Q1			UNIT	
			MIN	TYP	MAX	MIN	TYP	MAX		
SR+ Positive slew rate	$V_O(PP) = 10$ V, $A_{VD} = -1$, $R_L = 2$ kΩ, $C_L = 100$ pF, See Figure 1	25°C	30	40		30	40		V/μs	
		Full range	22			22				
SR- Negative slew rate		25°C	30	45		30	45		V/μs	
		Full range	22			22				
t_s Settling time	$A_{VD} = -1$, 10-V step, $R_L = 1$ kΩ, $C_L = 100$ pF	To 10 mV	25°C	0.4		0.4			μs	
		To 1 mV		1.5		1.5				
V_n Equivalent input noise voltage	$R_S = 20$ Ω, See Figure 3	$f = 10$ Hz	25°C	28	55	28	55		nV/√Hz	
		$f = 10$ kHz		11.6	17	11.6	17			
$V_{N(PP)}$ Peak-to-peak equivalent input noise voltage		$f = 10$ Hz to 10 kHz	25°C	6		6			μV	
		$f = 0.1$ Hz to 10 Hz		0.6		0.6				
I_n Equivalent input noise current	$V_{IC} = 0$, $f = 10$ kHz	25°C		2.8		2.8			fA/√Hz	
THD + N Total harmonic distortion plus noise	$V_O(PP) = 20$ V, $A_{VD} = 10$, $f = 1$ kHz, $R_L = 2$ kΩ, $R_S = 25$ Ω	25°C		0.008%		0.008%				
B_1 Unity-gain bandwidth	$V_I = 10$ mV, $C_L = 25$ pF, See Figure 2	25°C		8	10	8	10		MHz	
B_{OM} Maximum output-swing bandwidth	$V_O(PP) = 20$ V, $A_{VD} = -1$, $R_L = 2$ kΩ, $C_L = 25$ pF	25°C		478	637	478	637		kHz	
ϕ_m Phase margin at unity gain	$V_I = 10$ mV, $C_L = 25$ pF, See Figure 2	25°C		57		57				

† Full range is -40°C to 125°C.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2072-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2072-Q1			TLE2072A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{IO}	Input offset voltage $V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$,	25°C	0.9	6		0.65	3.5		mV
α_{VIO}		Full range		10			8		
I_{IO}	Input offset current $V_{IC} = 0$, $V_O = 0$, See Figure 4	25°C	5	100		5	100	pA	
I_{IB}		Full range		20			20	nA	
		25°C	15	175		15	175	pA	
		Full range		60			60	nA	
V_{ICR}	Common-mode input voltage range $R_S = 50 \Omega$	25°C	5 to -1	5 to -1.9		5 to -1	5 to -1.9		V
		Full range	5 to -0.8			5 to -0.8			
V_{OM+}	Maximum positive peak output voltage swing $I_O = -200 \mu A$	25°C	3.8	4.1		3.8	4.1		V
		Full range	3.6			3.6			
		25°C	3.5	3.9		3.5	3.9		
		Full range	3.3			3.3			
		25°C	1.5	2.3		1.5	2.3		
		Full range	1.4			1.4			
V_{OM-}	Maximum negative peak output voltage swing $I_O = 200 \mu A$	25°C	-3.8	-4.2		-3.8	-4.2		V
		Full range	-3.6			-3.6			
		25°C	-3.5	-4.1		-3.5	-4.1		
		Full range	-3.3			-3.3			
		25°C	-1.5	-2.4		-1.5	-2.4		
		Full range	-1.4			-1.4			
A_{VD}	Large-signal differential voltage amplification $V_O = \pm 2.3$ V	$R_L = 600 \Omega$	25°C	80	91	80	91		dB
			Full range	78		78			
		$R_L = 2 k\Omega$	25°C	90	100	90	100		
			Full range	88		88			
		$R_L = 10 k\Omega$	25°C	95	106	95	106		
			Full range	93		93			
r_i	Input resistance	$V_{IC} = 0$	25°C	10^{12}		10^{12}		Ω	
c_i	Input capacitance See Figure 5	$V_{IC} = 0$, Common mode	25°C	11		11			pF
z_o			25°C	2.5		2.5			
$CMRR$	Common-mode rejection ratio	$V_{IC} = V_{ICR\min}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	70	89	70	89		dB
			Full range	68		68			

[†] Full range is -40°C to 125°C.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLE207x-Q1, TLE207xA-Q1
**EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**
SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2072-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V (unless otherwise noted) (continued)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2072-Q1			TLE2072A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
k_{SVR}	Supply-voltage rejection ratio ($\Delta V_{CC\pm} / \Delta V_{IO}$)	$V_{CC\pm} = \pm 5$ V to ± 15 V, $V_O = 0$, $R_S = 50 \Omega$	Full range	80		80			dB
I_{CC}	Supply current (both channels)	$V_O = 0$, No load	25°C	2.7	2.9	3.6	2.7	2.9	3.6
			Full range		3.6		3.6		mA
a_x	Crosstalk attenuation	$V_{IC} = 0$, $R_L = 2 \text{ k}\Omega$	25°C	120		120			dB
I_{OS}	Short-circuit output current	$V_O = 0$	25°C		-35		-35		mA
					45		45		

† Full range is -40°C to 125°C.

TLE2072-Q1 operating characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2072-Q1			TLE2072A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
SR+	Positive slew rate	$V_O(\text{PP}) = \pm 2.3$ V, $A_{VD} = -1$, $C_L = 100 \text{ pF}$, See Figure 1	25°C	35		35			V/ μ s
			Full range	18		18			
SR-	Negative slew rate		25°C	38		38			V/ μ s
			Full range	18		18			
t_s	Settling time	$A_{VD} = -1$, 2-V step, $R_L = 1 \text{ k}\Omega$, $C_L = 100 \text{ pF}$	To 10 mV	25°C	0.25		0.25		μ s
			To 1 mV		0.4		0.4		
V_n	Equivalent input noise voltage		$f = 10 \text{ Hz}$	25°C	28	55	28	55	nV/ $\sqrt{\text{Hz}}$
			$f = 10 \text{ kHz}$		11.6	17	11.6	17	
$V_{N(\text{PP})}$	Peak-to-peak equivalent input noise voltage	$R_S = 20 \Omega$, See Figure 3	$f = 10 \text{ Hz}$ to 10 kHz	25°C	6		6		μ V
			$f = 0.1 \text{ Hz}$ to 10 Hz		0.6		0.6		
I_n	Equivalent input noise current	$V_{IC} = 0$,	$f = 10 \text{ kHz}$	25°C	2.8		2.8		fA/ $\sqrt{\text{Hz}}$
THD + N	Total harmonic distortion plus noise	$V_O(\text{PP}) = 5$ V, $f = 1 \text{ kHz}$, $R_S = 25 \Omega$	$A_{VD} = 10$, $R_L = 2 \text{ k}\Omega$,	25°C	0.013%		0.013%		
B_1	Unity-gain bandwidth	$V_I = 10 \text{ mV}$,	$R_L = 2 \text{ k}\Omega$, See Figure 2	25°C	9.4		9.4		MHz
B_{OM}	Maximum output-swing bandwidth	$V_O(\text{PP}) = 4$ V, $R_L = 2 \text{ k}\Omega$,	$A_{VD} = -1$, $C_L = 25 \text{ pF}$	25°C	2.8		2.8		MHz
ϕ_m	Phase margin at unity gain	$V_I = 10 \text{ mV}$,	$R_L = 2 \text{ k}\Omega$, See Figure 2	25°C	56		56		

† Full range is -40°C to 125°C.



**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2072-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2072-Q1			TLE2072A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{IO} Input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$	25°C	1.1	6		0.7	3.5		mV
		Full range		10			8		
		Full range		2.4		2.4	20		
α_{VIO} Temperature coefficient of input offset voltage									$\mu\text{V}/^\circ\text{C}$
I_{IO} Input offset current	$V_{IC} = 0$, $V_O = 0$, See Figure 4	25°C	6	100		6	100		pA
		Full range		20			20		nA
		25°C	20	175		20	175		pA
I_{IB} Input bias current		Full range		60			60		nA
V_{ICR} Common-mode input voltage range	$R_S = 50 \Omega$	25°C	15	15		15	15		V
			to -11	to -11.9		to -11	to -11.9		
		Full range	15			15			
			to -10.8			to -10.8			
V_{OM+} Maximum positive peak output voltage swing	$I_O = -200 \mu\text{A}$	25°C	13.8	14.1		13.8	14.1		V
		Full range	13.6			13.6			
	$I_O = -2 \text{ mA}$	25°C	13.5	13.9		13.5	13.9		
		Full range	13.3			13.3			
	$I_O = -20 \text{ mA}$	25°C	11.5	12.3		11.5	12.3		
		Full range	11.4			11.4			
V_{OM-} Maximum negative peak output voltage swing	$I_O = 200 \mu\text{A}$	25°C	-13.8	-14.2		-13.8	-14.2		V
		Full range	-13.6			-13.6			
	$I_O = 2 \text{ mA}$	25°C	-13.5	-14		-13.5	-14		
		Full range	-13.3			-13.3			
	$I_O = 20 \text{ mA}$	25°C	-11.5	-12.4		-11.5	-12.4		
		Full range	-11.4			-11.4			
A_{VD} Large-signal differential voltage amplification	$V_O = \pm 10 \text{ V}$	$R_L = 600 \Omega$	25°C	80	96	80	96		dB
			Full range	78		78			
		$R_L = 2 \text{ k}\Omega$	25°C	90	109	90	109		
	$R_L = 10 \text{ k}\Omega$	Full range	89			89			
		25°C	95	118		95	118		
		Full range	93			93			
r_i Input resistance	$V_{IC} = 0$	25°C	10 ¹²			10 ¹²			Ω
c_i Input capacitance	$V_{IC} = 0$, See Figure 5	Common mode	25°C		7.5		7.5		pF
		Differential	25°C		2.5		2.5		
z_o Open-loop output impedance	$f = 1 \text{ MHz}$	25°C		80			80		Ω
CMRR Common-mode rejection ratio	$V_{IC} = V_{ICR\min}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	80	98		80	98		dB
		Full range	78			78			
k_{SVR} Supply-voltage rejection ratio ($\Delta V_{CC\pm}/\Delta V_{IO}$)	$V_{CC\pm} = \pm 5 \text{ V to } \pm 15 \text{ V}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	82	99		82	99		dB
		Full range	80			80			

[†] Full range is -40°C to 125°C.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLE207x-Q1, TLE207xA-Q1
**EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2072-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V (unless otherwise noted) (continued)

PARAMETER	TEST CONDITIONS	TA [†]	TLE2072-Q1			TLE2072A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
I _{CC}	Supply current (both channels) $V_O = 0$, No load	25°C	2.7	3.1	3.6	2.7	3.1	3.6	mA
		Full range			3.6			3.6	
a _X	Crosstalk attenuation $V_{IC} = 0$, $R_L = 2\text{ k}\Omega$	25°C		120			120		dB
I _{OS}	Short-circuit output current $V_O = 0$	25°C	-30	-45		-30	-45		mA
			30	48		30	48		

[†] Full range is -40°C to 125°C.

TLE2072-Q1 operating characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V

PARAMETER	TEST CONDITIONS	TA [†]	TLE2072-Q1			TLE2072A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
SR+	Positive slew rate $V_O(\text{PP}) = 10\text{ V}$, $A_{VD} = -1$, $R_L = 2\text{ k}\Omega$, $C_L = 100\text{ pF}$, See Figure 1	25°C	28	40		28	40		V/ μ s
		Full range	20			20			
SR-	Negative slew rate $A_{VD} = -1$, 10-V step, $R_L = 1\text{ k}\Omega$, $C_L = 100\text{ pF}$	25°C	30	45		30	45		V/ μ s
		Full range	20			20			
t _S	Settling time $A_{VD} = -1$, 10-V step, $R_L = 1\text{ k}\Omega$, $C_L = 100\text{ pF}$	To 10 mV To 1 mV	25°C	0.4		0.4			μ s
				1.5		1.5			
V _n	Equivalent input noise voltage	$f = 10\text{ Hz}$ $f = 10\text{ kHz}$	25°C	28	55	28	55		nV/ $\sqrt{\text{Hz}}$
				11.6	17	11.6	17		
V _{N(PP)}	Peak-to-peak equivalent input noise voltage $R_S = 20\text{ }\Omega$, See Figure 3	$f = 10\text{ Hz}$ to 10 kHz $f = 0.1\text{ Hz}$ to 10 Hz	25°C	6		6			μ V
				0.6		0.6			
I _n	Equivalent input noise current $V_{IC} = 0$, $f = 10\text{ kHz}$	25°C		2.8		2.8			fA/ $\sqrt{\text{Hz}}$
THD + N	Total harmonic distortion plus noise $V_O(\text{PP}) = 20\text{ V}$, $A_{VD} = 10$, $f = 1\text{ kHz}$, $R_L = 2\text{ k}\Omega$, $R_S = 25\text{ }\Omega$	25°C		0.008%		0.008%			
B ₁	Unity-gain bandwidth $V_I = 10\text{ mV}$, $R_L = 2\text{ k}\Omega$, $C_L = 25\text{ pF}$, See Figure 2	25°C	8	10		8	10		MHz
B _{OM}	Maximum output-swing bandwidth $V_O(\text{PP}) = 20\text{ V}$, $A_{VD} = -1$, $R_L = 2\text{ k}\Omega$, $C_L = 25\text{ pF}$	25°C	478	637		478	637		kHz
ϕ_m	Phase margin at unity gain $V_I = 10\text{ mV}$, $R_L = 2\text{ k}\Omega$, $C_L = 25\text{ pF}$, See Figure 2	25°C		57		57			

[†] Full range is -40°C to 125°C.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2074-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2074-Q1			TLE2074A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{IO} Input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50\Omega$	25°C	-1.6	7		-0.5	4		mV
		Full range		11			9		
α_{VIO} Temperature coefficient of input offset voltage		Full range		10.1		10.1	30		$\mu\text{V}/^\circ\text{C}$
I_{IO} Input offset current	$V_{IC} = 0$, $V_O = 0$, See Figure 4	25°C	15	100		15	100		pA
		Full range		20			20		
I_{IB} Input bias current		25°C	20	175		20	175		pA
		Full range		60			60		
V_{ICR} Common-mode input voltage range	$R_S = 50\Omega$	25°C	5 to -1	5 to -1.9		5 to -1	5 to -1.9		V
		Full range	5 to -0.8			5 to -0.8			
V_{OM+} Maximum positive peak output voltage swing	$I_O = -200\mu\text{A}$	25°C	3.8	4.1		3.8	4.1		V
		Full range	3.6			3.6			
	$I_O = -2\text{ mA}$	25°C	3.5	3.9		3.5	3.9		
		Full range	3.3			3.3			
	$I_O = -20\text{ mA}$	25°C	1.5	2.3		1.5	2.3		
		Full range	1.4			1.4			
V_{OM-} Maximum negative peak output voltage swing	$I_O = 200\mu\text{A}$	25°C	-3.8	-4.2		-3.8	-4.2		V
		Full range	-3.6			-3.6			
	$I_O = 2\text{ mA}$	25°C	-3.5	-4.1		-3.5	-4.1		
		Full range	-3.3			-3.3			
	$I_O = 20\text{ mA}$	25°C	-1.5	-2.4		-1.5	-2.4		
		Full range	-1.4			-1.4			
A_{VD} Large-signal differential voltage amplification	$V_O = \pm 2.3\text{ V}$	$R_L = 600\Omega$	25°C	80	91	80	91		dB
			Full range	78		78			
		$R_L = 2\text{ k}\Omega$	25°C	90	100	90	100		
			Full range	88		88			
		$R_L = 10\text{ k}\Omega$	25°C	95	106	95	106		
			Full range	93		93			
r_i Input resistance	$V_{IC} = 0$	25°C		10^{12}		10^{12}			Ω
c_i Input capacitance	Common mode Differential	$V_{IC} = 0$, See Figure 5	25°C	11		11			pF
			25°C	2.5		2.5			
z_o Open-loop output impedance	$f = 1\text{ MHz}$	25°C	80			80			Ω
CMRR Common-mode rejection ratio	$V_{IC} = V_{ICR\min}$, $V_O = 0$, $R_S = 50\Omega$	25°C	70	89		70	89		dB
		Full range	68			68			
k_{SVR} Supply-voltage rejection ratio ($\Delta V_{CC\pm}/\Delta V_{IO}$)	$V_{CC\pm} = \pm 5\text{ V to } \pm 15\text{ V}$, $V_O = 0$, $R_S = 50\Omega$	25°C	82	99		82	99		dB
		Full range	80			80			

† Full range is -40°C to 125°C .



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLE207x-Q1, TLE207xA-Q1
**EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**
SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2074-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V (unless otherwise noted) (continued)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2074-Q1			TLE2074A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
I_{CC}	$V_O = 0$, No load	25°C	5.2	6.3	7.5	5.2	6.3	7.5	mA
		Full range			7.5			7.5	
Crosstalk attenuation	$V_{IC} = 0$, $R_L = 2$ kΩ	25°C		120			120		dB
I_{OS}	$V_O = 0$	$V_{ID} = 1$ V $V_{ID} = -1$ V	25°C		-35		-35		mA
					45		45		

† Full range is -40°C to 125°C .

TLE2074-Q1 operating characteristics at specified free-air temperature, $V_{CC\pm} = \pm 5$ V

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2074-Q1			TLE2074A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
SR+	Positive slew rate $V_O(\text{PP}) = \pm 2.3$ V, $\text{AVD} = -1$, $C_L = 100$ pF, $R_L = 2$ kΩ, See Figure 1	25°C		35			35		V/μs
		Full range		18			18		
SR-	Negative slew rate $\text{AVD} = -1$, 2-V step, $R_L = 1$ kΩ, $C_L = 100$ pF	25°C		38			38		V/μs
		Full range		18			18		
t_s	Settling time $\text{AVD} = -1$, 2-V step, $R_L = 1$ kΩ, $C_L = 100$ pF	To 10 mV To 1 mV	25°C		0.25		0.25		μs
					0.4		0.4		
V_n	Equivalent input noise voltage $R_S = 20$ Ω, See Figure 3	$f = 10$ Hz $f = 10$ kHz	25°C	28	55	28	55		nV/√Hz
				11.6	17	11.6	17		
$V_{N(\text{PP})}$	Peak-to-peak equivalent input noise voltage $R_S = 20$ Ω, See Figure 3	$f = 10$ Hz to 10 kHz $f = 0.1$ Hz to 10 Hz	25°C		6		6		μV
					0.6		0.6		
I_n	Equivalent input noise current $V_{IC} = 0$, $f = 10$ kHz		25°C		2.8		2.8		fA/√Hz
THD + N	Total harmonic distortion plus noise $V_O(\text{PP}) = 5$ V, $f = 1$ kHz, $R_S = 25$ Ω	$A_{\text{VD}} = 10$, $R_L = 2$ kΩ,	25°C		0.013%		0.013%		
B_1	Unity-gain bandwidth $V_I = 10$ mV, $C_L = 25$ pF,	$R_L = 2$ kΩ, See Figure 2	25°C		9.4		9.4		MHz
B_{OM}	Maximum output-swing bandwidth $V_O(\text{PP}) = 4$ V, $R_L = 2$ kΩ,	$A_{\text{VD}} = -1$, $C_L = 25$ pF	25°C		2.8		2.8		MHz
f_m	Phase margin at unity gain $V_I = 10$ mV, $C_L = 25$ pF,	$R_L = 2$ kΩ, See Figure 2	25°C		56		56		

† Full range is -40°C to 125°C .

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2074-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	TA†	TLE2074-Q1			TLE2074A-Q1			UNIT	
			MIN	TYP	MAX	MIN	TYP	MAX		
V_{IO} Input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$	25°C	-1.6	7		-0.5	4		mV	
		Full range		11			9			
		Full range		10.1		10.1	30			
α_{VIO} Temperature coefficient of input offset voltage									$\mu\text{V}/^\circ\text{C}$	
I_{IO} Input offset current	$V_{IC} = 0$, $V_O = 0$, See Figure 4	25°C	15	100		15	100		pA	
		Full range		20			20		nA	
I_{IB} Input bias current		25°C	25	175		25	175		pA	
		Full range		60			60		nA	
V_{ICR} Common-mode input voltage range	$R_S = 50 \Omega$	25°C	15	15		15	15		V	
		to	to			to	to			
		-11	-11.9			-11	-11.9			
V_{OM+} Maximum positive peak output voltage swing	$I_O = -200 \mu\text{A}$	Full range	15			15			V	
			to			to				
		-10.8				-10.8				
V_{OM-} Maximum negative peak output voltage swing	$I_O = -2 \text{ mA}$	25°C	13.8	14.1		13.8	14.1		V	
		Full range	13.6			13.6				
		25°C	13.5	13.9		13.5	13.9			
V_{OM-} Maximum negative peak output voltage swing	$I_O = -20 \text{ mA}$	Full range	13.3			13.3			V	
		25°C	11.5	12.3		11.5	12.3			
		Full range	11.4			11.4				
A_{VD} Large-signal differential voltage amplification	$V_O = \pm 10 \text{ V}$	25°C	-13.8	-14.2		-13.8	-14.2		dB	
		Full range	-13.6			-13.6				
		25°C	-13.5	-14		-13.5	-14			
A_{VD} Large-signal differential voltage amplification	$I_O = 2 \text{ mA}$	Full range	-13.3			-13.3			V	
		25°C	-11.5	-12.4		-11.5	-12.4			
		Full range	-11.4			-11.4				
r_i Input resistance	$V_{IC} = 0$	$R_L = 600 \Omega$	25°C	80	96	80	96		dB	
			Full range	78		78				
			25°C	90	109	90	109			
c_i Input capacitance	$V_{IC} = 0$, See Figure 5	$R_L = 2 \text{ k}\Omega$	Full range	88		88			pF	
			25°C	95	118	95	118			
			Full range	93		93				
z_o Open-loop output impedance	$f = 1 \text{ MHz}$		25°C	80		80			Ω	
$CMRR$ Common-mode rejection ratio	$V_{IC} = V_{ICR\min}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	80	98		80	98		dB	
		Full range	78			78				
k_{SVR} Supply-voltage rejection ratio ($\Delta V_{CC\pm} / \Delta V_{IO}$)	$V_{CC\pm} = \pm 5 \text{ V to } \pm 15 \text{ V}$, $V_O = 0$, $R_S = 50 \Omega$	25°C	82	99		82	99		dB	
		Full range	80			80				

† Full range is -40°C to 125°C .



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLE207x-Q1, TLE207xA-Q1
**EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TLE2074-Q1 electrical characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V (unless otherwise noted) (continued)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2074-Q1			TLE2074A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
I_{CC}	$V_O = 0$, No load	25°C	5.2	6.5	7.5	5.2	6.5	7.5	mA
		Full range			7.5			7.5	
Crosstalk attenuation	$V_{IC} = 0$, $R_L = 2$ kΩ	25°C		120			120		dB
I_{OS}	$V_O = 0$	25°C	-30	-45		-30	-45		mA
			30	48		30	48		

† Full range is -40°C to 125°C.

TLE2074-Q1 operating characteristics at specified free-air temperature, $V_{CC\pm} = \pm 15$ V


PARAMETER	TEST CONDITIONS	T_A^\dagger	TLE2074-Q1			TLE2074A-Q1			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
SR+	Positive slew rate	$V_O(PP) = 10$ V, $A_{VD} = -1$, $R_L = 2$ kΩ, $C_L = 100$ pF, See Figure 1	25°C	25	40	25	40		V/μs
			Full range		17		17		
SR-	Negative slew rate		25°C	30	45	30	45		V/μs
			Full range		20		20		
t_s	Settling time	$A_{VD} = -1$, 10-V step, $R_L = 1$ kΩ, $C_L = 100$ pF	To 10 mV	25°C	0.4	0.4			μs
			To 1 mV		1.5	1.5			
V_n	Equivalent input noise voltage		$f = 10$ Hz	25°C	28	55	28	55	nV/ $\sqrt{\text{Hz}}$
			$f = 10$ kHz		11.6	17	11.6	17	
$V_{N(PP)}$	Peak-to-peak equivalent input noise voltage	$R_S = 20$ Ω, See Figure 3	$f = 10$ Hz to 10 kHz	25°C	6	6			μV
			$f = 0.1$ Hz to 10 Hz		0.6	0.6			
I_n	Equivalent input noise current	$V_{IC} = 0$, $f = 10$ kHz	25°C		2.8		2.8		fA/ $\sqrt{\text{Hz}}$
THD + N	Total harmonic distortion plus noise	$V_O(PP) = 20$ V, $A_{VD} = 10$, $f = 1$ kHz, $R_L = 2$ kΩ, $R_S = 25$ Ω	25°C		0.008%		0.008%		
B_1	Unity-gain bandwidth	$V_I = 10$ mV, $R_L = 2$ kΩ, $C_L = 25$ pF, See Figure 2	25°C		8	10	8	10	MHz
B_{OM}	Maximum output-swing bandwidth	$V_O(PP) = 20$ V, $A_{VD} = -1$, $R_L = 2$ kΩ, $C_L = 25$ pF	25°C		478	637	478	637	kHz
ϕ_m	Phase margin at unity gain	$V_I = 10$ mV, $R_L = 2$ kΩ, $C_L = 25$ pF, See Figure 2	25°C		57		57		

† Full range is -40°C to 125°C.

TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS


SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

PARAMETER MEASUREMENT INFORMATION



† Includes fixture capacitance

Figure 1. Slew-Rate Test Circuit



† Includes fixture capacitance

Figure 2. Unity-Gain Bandwidth and Phase-Margin Test Circuit




Figure 3. Noise-Voltage Test Circuit




Figure 4. Input-Bias and Offset-Current Test Circuit




Figure 5. Internal Input Capacitance

typical values

Typical values presented in this data sheet represent the median (50% point) of device parametric performance.

input bias and offset current

At the picoampere bias current typical of the TLE207x and TLE207xA, accurate measurement of the bias current becomes difficult. Not only does this measurement require a picoammeter but test socket leakages can easily exceed the actual device bias currents. To accurately measure these small currents, Texas Instruments uses a two-step process. The socket leakage is measured using picoammeters with bias voltages applied but with no device in the socket. The device is then inserted in the socket and a second test is performed that measures both the socket leakage and the device input bias current. The two measurements are then subtracted algebraically to determine the bias current of the device.

TYPICAL CHARACTERISTICS

Table of Graphs

			FIGURE
V_{IO}	Input offset voltage	Distribution	6, 7, 8
αV_{IO}	Temperature coefficient of input offset voltage	Distribution	9, 10, 11
I_{IO}	Input offset current	vs Free-air temperature	12, 13
I_{IB}	Input bias current	vs Free-air temperature vs Total supply voltage	12, 13 14
V_{ICR}	Common-mode input voltage range	vs Free-air temperature	15
V_O	Output voltage	vs Differential input voltage	16, 17
V_{OM+}	Maximum positive peak output voltage	vs Output current	18
V_{OM-}	Maximum negative peak output voltage	vs Output current	19
V_{OM}	Maximum peak output voltage	vs Free-air temperature vs Supply voltage	20, 21 22
$V_O(PP)$	Maximum peak-to-peak output voltage	vs Frequency	23
V_O	Output voltage	vs Settling time	24
AVD	Large-signal differential voltage amplification	vs Load resistance vs Free-air temperature	25 26, 27
AVD	Small-signal differential voltage amplification	vs Frequency	28, 29
CMRR	Common-mode rejection ratio	vs Frequency vs Free-air temperature	30 31
kSVR	Supply-voltage rejection ratio	vs Frequency vs Free-air temperature	32 33
I_{CC}	Supply current	vs Supply voltage vs Free-air temperature vs Differential input voltage	34, 35, 36 37, 38, 39 40 – 45
I_{OS}	Short-circuit output current	vs Supply voltage vs Elapsed time vs Free-air temperature	46 47 48
SR	Slew rate	vs Free-air temperature vs Load resistance vs Differential input voltage	49, 50 51 52
V_n	Equivalent Input noise voltage (spectral density)	vs Frequency	53
V_n	Input referred noise voltage	vs Noise bandwidth Over a 10-second time interval	54 55
	Third-octave spectral noise density	vs Frequency bands	56
THD + N	Total harmonic distortion plus noise	vs Frequency	57, 58
B_1	Unity-gain bandwidth	vs Load capacitance	59
	Gain-bandwidth product	vs Free-air temperature vs Supply voltage	60 61
	Gain margin	vs Load capacitance	62
ϕ_m	Phase margin	vs Free-air temperature vs Supply voltage vs Load capacitance	63 64 65
	Phase shift	vs Frequency	28, 29
	Noninverting large-signal pulse response	vs Time	66
	Small-signal pulse response	vs Time	67
z_o	Closed-loop output impedance	vs Frequency	68
	Crosstalk attenuation	vs Frequency	69

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS




Figure 6




Figure 7




Figure 8




Figure 9

TYPICAL CHARACTERISTICS

DISTRIBUTION OF TLE2072 INPUT OFFSET VOLTAGE TEMPERATURE COEFFICIENT




Figure 10

DISTRIBUTION OF TLE2074 INPUT OFFSET VOLTAGE TEMPERATURE COEFFICIENT




Figure 11

INPUT BIAS CURRENT AND INPUT OFFSET CURRENT† VS FREE-AIR TEMPERATURE




Figure 12

INPUT BIAS CURRENT AND INPUT OFFSET CURRENT† VS FREE-AIR TEMPERATURE








Figure 13

† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS



† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TYPICAL CHARACTERISTICS

MAXIMUM POSITIVE PEAK OUTPUT VOLTAGE[†]
vs
OUTPUT CURRENT




Figure 18

MAXIMUM NEGATIVE PEAK OUTPUT VOLTAGE[†]
vs
OUTPUT CURRENT




Figure 19

MAXIMUM PEAK OUTPUT VOLTAGE[†]
vs
FREE-AIR TEMPERATURE




Figure 20

MAXIMUM PEAK OUTPUT VOLTAGE[†]
vs
FREE-AIR TEMPERATURE








Figure 21

[†] Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS



† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TYPICAL CHARACTERISTICS




Figure 26




Figure 27

[†] Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS




Figure 28




Figure 29

TYPICAL CHARACTERISTICS




Figure 30




Figure 31




Figure 32




Figure 33

[†] Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS




Figure 34




Figure 35




Figure 36








Figure 37

† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TYPICAL CHARACTERISTICS



[†] Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS




Figure 42




Figure 43




Figure 44








Figure 45

TYPICAL CHARACTERISTICS



† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS




Figure 50




Figure 51




Figure 52




Figure 53

[†] Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TYPICAL CHARACTERISTICS




Figure 54




Figure 55




Figure 56




Figure 57

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS




Figure 58




Figure 59




Figure 60




Figure 61

† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

TYPICAL CHARACTERISTICS




Figure 62




Figure 63




Figure 64




Figure 65

[†] Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

**TLE207x-Q1, TLE207xA-Q1
EXCALIBUR LOW-NOISE HIGH-SPEED
JFET-INPUT OPERATIONAL AMPLIFIERS**

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

TYPICAL CHARACTERISTICS

**NONINVERTING LARGE-SIGNAL
PULSE RESPONSE†**




Figure 66

SMALL-SIGNAL PULSE RESPONSE




Figure 67

**CLOSED-LOOP OUTPUT IMPEDANCE
vs
FREQUENCY**




Figure 68

**TLE2072 AND TLE2074
CROSSTALK ATTENUATION
vs
FREQUENCY**




Figure 69

† Data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices.

APPLICATION INFORMATION

input characteristics

The TLE207x, TLE207xA, and TLE207xB are specified with a minimum and a maximum input voltage that if exceeded at either input could cause the device to malfunction. Because of the extremely high input impedance and resulting low bias current requirements, the TLE207x, TLE207xA, and TLE207xB are well suited for low-level signal processing; however, leakage currents on printed-circuit boards and sockets can easily exceed bias current requirements and cause degradation in system performance. It is good practice to include guard rings around inputs (see Figure 70). These guards should be driven from a low-impedance source at the same voltage level as the common-mode input.




Figure 70. Use of Guard Rings

TLE2071 input offset voltage nulling

The TLE2071 series offers external null pins that can be used to further reduce the input offset voltage. The circuit of Figure 71 can be connected as shown if the feature is desired. When external nulling is not needed, the null pins may be left unconnected.




Figure 71. Input Offset Voltage Nulling

TLE207x-Q1, TLE207xA-Q1 EXCALIBUR LOW-NOISE HIGH-SPEED JFET-INPUT OPERATIONAL AMPLIFIERS

SGLS226A – DECEMBER 2003 – REVISED AUGUST 2004

APPLICATION INFORMATION

macromodel information

Macromodel information provided was derived using *PSpice™ Parts™* model generation software. The Boyle macromodel (see Note 4) and subcircuit Figure 72 were generated using the TLE207x typical electrical and operating characteristics at $T_A = 25^\circ\text{C}$. Using this information, output simulations of the following key parameters can be generated to a tolerance of 20% (in most cases):

- Maximum positive output voltage swing
 - Maximum negative output voltage swing
 - Slew rate
 - Quiescent power dissipation
 - Input bias current
 - Open-loop voltage amplification
 - Unity-gain frequency
 - Common-mode rejection ratio
 - Phase margin
 - DC output resistance
 - AC output resistance
 - Short-circuit output current limit

NOTE 4: G.R. Boyle, B.M. Cohn, D. O. Pederson, and J. E. Solomon, "Macromodeling of Integrated Circuit Operational Amplifiers", *IEEE Journal of Solid-State Circuits*, SC-9, 353 (1974).




Figure 72. Boyle Macromodel and Subcircuit

PSpice and *Parts* are trademarks of MicroSim Corporation.

PACKAGING INFORMATION

Orderable Device	Status ⁽¹⁾	Package Type	Package Drawing	Pins	Package Qty	Eco Plan ⁽²⁾	Lead/Ball Finish	MSL Peak Temp ⁽³⁾
TLE2071AQDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLE2071QDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLE2072AQDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM
TLE2072QDRQ1	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-2-250C-1 YEAR/ Level-1-235C-UNLIM

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

⁽²⁾ Eco Plan - May not be currently available - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

None: Not yet available Lead (Pb-Free).

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Green (RoHS & no Sb/Br): TI defines "Green" to mean "Pb-Free" and in addition, uses package materials that do not contain halogens, including bromine (Br) or antimony (Sb) above 0.1% of total product weight.


⁽³⁾ MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDECindustry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

D (R-PDSO-G8)

PLASTIC SMALL-OUTLINE PACKAGE



4040047-2/F 07/2004

- NOTES:
- All linear dimensions are in inches (millimeters).
 - This drawing is subject to change without notice.
 - Body dimensions do not include mold flash or protrusion not to exceed 0.006 (0.15).
 - Falls within JEDEC MS-012 variation AA.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments
Post Office Box 655303 Dallas, Texas 75265

Copyright © 2005, Texas Instruments Incorporated