

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

- High Slew Rate . . . 10.5 V/ μ s Typ
- High-Gain Bandwidth . . . 5.1 MHz Typ
- Supply Voltage Range 2.5 V to 5.5 V
- Rail-to-Rail Output
- 360 μ V Input Offset Voltage
- Low Distortion Driving 600- Ω
0.005% THD+N
- 1 mA Supply Current (Per Channel)
- 17 nV/ $\sqrt{\text{Hz}}$ Input Noise Voltage
- 2 pA Input Bias Current
- Characterized From $T_A = -55^\circ\text{C}$ to 125°C
- Available in MSOP and SOT-23 Packages
- Micropower Shutdown Mode . . . $I_{DD} < 1 \mu\text{A}$
- Available in Q-Temp Automotive
High Reliability Automotive Applications
Configuration Control / Print Support
Qualification to Automotive Standards

description

The TLV277x CMOS operational amplifier family combines high slew rate and bandwidth, rail-to-rail output swing, high output drive, and excellent dc precision. The device provides 10.5 V/ μ s of slew rate and 5.1 MHz of bandwidth while only consuming 1 mA of supply current per channel. This ac performance is much higher than current competitive CMOS amplifiers. The rail-to-rail output swing and high output drive make these devices a good choice for driving the analog input or reference of analog-to-digital converters. These devices also have low distortion while driving a 600- Ω load for use in telecom systems.

These amplifiers have a 360- μ V input offset voltage, a 17 nV/ $\sqrt{\text{Hz}}$ input noise voltage, and a 2-pA input bias current for measurement, medical, and industrial applications. The TLV277x family is also specified across an extended temperature range (-40°C to 125°C), making it useful for automotive systems, and the military temperature range (-55°C to 125°C), for military systems.

These devices operate from a 2.5-V to 5.5-V single supply voltage and are characterized at 2.7 V and 5 V. The single-supply operation and low power consumption make these devices a good solution for portable applications. The following table lists the packages available.

FAMILY PACKAGE TABLE

DEVICE	NUMBER OF CHANNELS	PACKAGE TYPES								SHUTDOWN	UNIVERSAL EVM BOARD
		PDIP	CDIP	SOIC	SOT-23	TSSOP	MSOP	LCCC	CPAK		
TLV2770	1	8	—	8	—	—	8	—	—	Yes	Refer to the EVM Selection Guide (Lit# SLOU060)
TLV2771	1	—	—	8	5	—	—	—	—	—	
TLV2772	2	8	8	8	—	8	8	20	10	—	
TLV2773	2	14	—	14	—	—	10	—	—	Yes	
TLV2774	4	14	—	14	—	14	—	—	—	—	
TLV2775	4	16	—	16	—	16	—	—	—	Yes	

A SELECTION OF SINGLE-SUPPLY OPERATIONAL AMPLIFIER PRODUCTS†

DEVICE	V _{DD} (V)	BW (MHz)	SLEW RATE (V/ μ s)	I _{DD} (per channel) (μ A)	RAIL-TO-RAIL
TLV277X	2.5 – 6.0	5.1	10.5	1000	O
TLV247X	2.7 – 6.0	2.8	1.5	600	I/O
TLV245X	2.7 – 6.0	0.22	0.11	23	I/O
TLV246X	2.7 – 6.0	6.4	1.6	550	I/O

† All specifications measured at 5 V.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

This document contains information on products in more than one phase of development. The status of each device is indicated on the page(s) specifying its electrical characteristics.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

Copyright © 2001, Texas Instruments Incorporated
On products compliant to MIL-PRF-38535, all parameters are tested unless otherwise noted. On all other products, production processing does not necessarily include testing of all parameters.

**TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TLV2770 and TLV2771 AVAILABLE OPTIONS

TA	V_{IO} max AT 25°C (mV)	PACKAGED DEVICES			
		SMALL OUTLINE (D)	SOT-23 (DBV)	MSOP (DGK)	PLASTIC DIP (P)
0°C to 70°C	2.5	TLV2770CD TLV2771CD	— TLV2771CDBV	TLV2770CDGK† —	TLV2770CP —
–40°C to 125°C	2.5	TLV2770ID TLV2771ID	— TLV2771IDBV	TLV2770IDGK† —	TLV2770IP —
	1.6	TLV2770AID TLV2771AID	— —	— —	TLV2770AIP —

† This device is in the Product Preview stage of development. Please contact your local TI sales office for availability.

TLV2772 and TLV2773 AVAILABLE OPTIONS

TA	V_{IO} max AT 25°C (mV)	PACKAGED DEVICES				
		SMALL OUTLINE (D)	MSOP (DGK)	MSOP (DGS)	PLASTIC DIP (N)	PLASTIC DIP (P)
0°C to 70°C	2.5	TLV2772CD TLV2773CD	TLV2772CDGK —	— TLV2773CDGS	— TLV2773CN	TLV2772CP —
–40°C to 125°C	2.5	TLV2772ID TLV2773ID	TLV2772IDGK —	— TLV2773IDGS	— TLV2773IN	TLV2772IP —
	1.6	TLV2772AID TLV2773AID	— —	— —	— TLV2773AIN	TLV2772AIP —

TLV2774 and TLV2775 AVAILABLE OPTIONS

TA	V_{IO} max AT 25°C (mV)	PACKAGED DEVICES			
		SMALL OUTLINE (D)	PLASTIC DIP (N)	PLASTIC DIP (P)	TSSOP (PW)
0°C to 70°C	2.7	TLV2774CD TLV2775CD	— TLV2775CN	TLV2774CP —	TLV2774CPW TLV2775CPW
–40°C to 125°C	2.7	TLV2774ID TLV2775ID	— TLV2775IN	TLV2774IP —	TLV2774IPW TLV2775IPW
	2.1	TLV2774AID TLV2775AID	— TLV2775AIN	TLV2774AIP —	TLV2774AIPW TLV2775AIPW

TLV2772M/Q AND TLV2772AM/Q AVAILABLE OPTIONS

TA	V_{IO} max AT 25°C (mV)	PACKAGED DEVICES				
		SMALL OUTLINE (D)	CHIP CARRIER (FK)	CERAMIC DIP (JG)	CERAMIC FLATPACK (U)	TSSOP (PW)
–40°C to 125°C	2.5	TLV2772QD‡	—	—	—	TLV2772QPW‡
	1.6	TLV2772AQD‡	—	—	—	TLV2772AQPW‡
–55°C to 125°C	2.5	TLV2772MD	TLV2772MFK	TLV2772MJG	TLV2772MU	—
	1.6	TLV2772AMD	TLV2772AMFK	TLV2772AMJG	TLV2772AMU	—

‡ Available in tape and reel



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

PACKAGE SYMBOLS











PACKAGE TYPE	PINS	PART NUMBER	SYMBOL [†]
SOT23	5 Pin	TLV2771CDBV	VAMC
		TLV2771IDBV	VAMI
MSOP	8 Pin	TLV2770CDGK	xxTIABO
		TLV2770IDGK	xxTIABP
		TLV2772CDGK	xxTIAAF
		TLV2772IDGK	xxTIAAG
	10 Pin	TLV2773CDGS	xxTIABQ
		TLV2773IDGS	xxTIABR

[†] xx represents the device date code.

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TLV277x PACKAGE PINOUTS



NC – No internal connection

† This device is in the Product Preview stage of development. Please contact your local TI sales office for availability.

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
 OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage, V_{DD} (see Note 1)	7 V
Differential input voltage, V_{ID} (see Note 2)	$\pm V_{DD}$
Input voltage range, V_I (any input, see Note 1)	-0.3 V to V_{DD}
Input current, I_I (any input)	± 4 mA
Output current, I_O	± 50 mA
Total current into V_{DD+}	± 50 mA
Total current out of GND	± 50 mA
Duration of short-circuit current (at or below) 25°C (see Note 3)	unlimited
Continuous total power dissipation	See Dissipation Rating Table
Operating free-air temperature range, T_A :	C suffix	0°C to 70°C
	I suffix	-40°C to 125°C
	Q suffix	-40°C to 125°C
	M suffix	-55°C to 125°C
Storage temperature range, T_{STG}	-65°C to 150°C
Lead temperature 1.6 mm (1/16 inch) from case for 10 seconds	260°C

† Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- NOTES: 1. All voltage values, except differential voltages, are with respect to GND.
 2. Differential voltages are at the noninverting input with respect to the inverting input. Excessive current flows when input is brought below GND - 0.3 V.
 3. The output may be shorted to either supply. Temperature and/or supply voltages must be limited to ensure that the maximum dissipation rating is not exceeded.

DISSIPATION RATING TABLE

PACKAGE	$T_A \leq 25^\circ\text{C}$ POWER RATING	DERATING FACTOR ABOVE $T_A = 25^\circ\text{C}$	$T_A = 70^\circ\text{C}$ POWER RATING	$T_A = 85^\circ\text{C}$ POWER RATING	$T_A = 125^\circ\text{C}$ POWER RATING
D	725 mW	5.8 mW/ $^\circ\text{C}$	464 mW	377 mW	145 mW
DBV	437 mW	3.5 mW/ $^\circ\text{C}$	280 mW	227 mW	87 mW
DGK	424 mW	3.4 mW/ $^\circ\text{C}$	271 mW	220 mW	85 mW
DGS	424 mW	3.4 mW/ $^\circ\text{C}$	271 mW	220 mW	85 mW
FK	1375 mW	11.0 mW/ $^\circ\text{C}$	672 mW	546 mW	210 mW
JG	1050 mW	8.4 mW/ $^\circ\text{C}$	880 mW	714 mW	275 mW
N	1150 mW	9.2 mW/ $^\circ\text{C}$	736 mW	598 mW	230 mW
P	1000 mW	8.0 mW/ $^\circ\text{C}$	640 mW	520 mW	200 mW
PW	700 mW	5.6 mW/ $^\circ\text{C}$	448 mW	364 mW	140 mW
U	675 mW	5.4 mW/ $^\circ\text{C}$	432 mW	350 mW	135 mW

recommended operating conditions

	C SUFFIX		I SUFFIX		Q SUFFIX		M SUFFIX		UNIT
	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	
Supply voltage, V_{DD}	2.5	6	2.5	6	2.5	6	2.5	6	V
Input voltage range, V_I	GND	$V_{DD+} - 1.3$	V						
Common-mode input voltage, V_{IC}	GND	$V_{DD+} - 1.3$	V						
Operating free-air temperature, T_A	0	70	-40	125	-40	125	-55	125	°C



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

electrical characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xC			UNIT	
				MIN	TYP	MAX		
V_{IO}	Input offset voltage	$V_{IC} = 0$, $R_S = 50 \Omega$, $V_O = 0$, $V_{DD} = \pm 1.35$ V	25°C	0.44	2.5		mV	
			Full range	0.47	2.7			
	TLV2773/4/5		25°C	0.8	2.7			
			Full range	0.86	2.9			
αV_{IO}	Temperature coefficient of input offset voltage	$V_{IC} = 0$, $R_S = 50 \Omega$, $V_O = 0$, $V_{DD} = \pm 1.35$ V	25°C to 125°C	2			$\mu\text{V}/^\circ\text{C}$	
I_{IO}	Input offset current		25°C	1	60		pA	
			Full range	2	100			
	Input bias current		25°C	2	60			
			Full range	6	100			
V_{ICR}	Common-mode input voltage range	CMRR > 70 dB, $R_S = 50 \Omega$	25°C	0 to 1.4	-0.3 to 1.7		V	
			Full range	0 to 1.4	-0.3 to 1.7			
V_{OH}	High-level output voltage	$I_{OH} = -0.675$ mA	25°C	2.6			V	
			Full range	2.5				
		$I_{OH} = -2.2$ mA	25°C	2.4				
			Full range	2.1				
V_{OL}	Low-level output voltage	$V_{IC} = 1.35$ V, $I_{OL} = 0.675$ mA	25°C	0.1			V	
			Full range	0.2				
		$V_{IC} = 1.35$ V, $I_{OL} = 2.2$ mA	25°C	0.21				
			Full range	0.6				
A_{VD}	Large-signal differential voltage amplification	$V_{IC} = 1.35$ V, $R_L = 10$ k Ω , $V_O = 0.6$ V to 2.1 V	25°C	20	380		V/mV	
			Full range	13				
$r_{i(d)}$	Differential input resistance		25°C	10 ¹²			Ω	
$C_{i(c)}$	Common-mode input capacitance	$f = 10$ kHz	25°C	8			pF	
Z_0	Closed-loop output impedance	$f = 100$ kHz, $A_V = 10$	25°C	25			Ω	
CMRR	Common-mode rejection ratio	$V_{IC} = 0$ to 1.5 V, $R_S = 50 \Omega$	25°C	70	84		dB	
			Full range	70	82			
k_{SVR}	Supply voltage rejection ratio ($\Delta V_{DD} / \Delta V_{IO}$)	$V_{DD} = 2.7$ V to 5 V, No load	25°C	70	89		dB	
			Full range	70	84			
I_{DD}	Supply current (per channel)	$V_O = 1.5$ V, No load	25°C	1	2		mA	
			Full range		2			
$I_{DD(SHDN)}$	Supply current in shutdown (per channel)		25°C	0.8	1.5		μA	
			Full range	1.3	2			
$V_{(ON)}$	Turnon voltage level	$A_V = 5$	25°C	1.47			V	
				1.43				
				1.40				
$V_{(OFF)}$	Turnoff voltage level	$A_V = 5$	25°C	1.27			V	
				1.21				
				1.20				

[†] Full range is 0°C to 70°C.

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

operating characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLV277xC			UNIT
			MIN	TYP	MAX	
SR Slew rate at unity gain	$V_{O(PP)} = 0.8$ V, $C_L = 100$ pF, $R_L = 10$ k Ω	25°C	5	9		V/ μ s
		Full range	4.7	6		
V_n Equivalent input noise voltage	f = 1 kHz	25°C	21			nV/ $\sqrt{\text{Hz}}$
	f = 10 kHz	25°C	17			
$V_{N(PP)}$ Peak-to-peak equivalent input noise voltage	f = 0.1 Hz to 1 Hz	25°C	0.33			μ V
	f = 0.1 Hz to 10 Hz		0.86			
I_n Equivalent input noise current	f = 100 Hz	25°C	0.6			fA/ $\sqrt{\text{Hz}}$
THD + N Total harmonic distortion plus noise	$R_L = 600$ Ω , f = 1 kHz	A $V = 1$	0.0085%			
		A $V = 10$	0.025%			
		A $V = 100$	0.12%			
Gain-bandwidth product	f = 10 kHz, $C_L = 100$ pF	$R_L = 600$ Ω ,	25°C	4.8		MHz
t_s Settling time	$A_V = -1$, Step = 1 V, $R_L = 600$ Ω , $C_L = 100$ pF	0.1%	25°C	0.186		μ s
		0.01%	25°C	0.3		
ϕ_m Phase margin at unity gain	$R_L = 600$ Ω ,	$C_L = 100$ pF	25°C	46°		
			25°C	12		
Gain margin						

[†] Full range is 0°C to 70°C.



TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

electrical characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xC			UNIT		
				MIN	TYP	MAX			
V_{IO}	Input offset voltage	$V_{IC} = 0$, $R_S = 50 \Omega$	$V_O = 0$, $V_{DD} = \pm 2.5$ V	25°C	0.36	2.5	mV		
				Full range	0.4	2.7			
	TLV2773/4/5			25°C	0.7	2.5			
				Full range	0.78	2.7			
α_{VIO}	Temperature coefficient of input offset voltage	$V_{IC} = 0$, $R_S = 50 \Omega$	$V_O = 0$, $V_{DD} = \pm 2.5$ V	25°C to 125°C	2		$\mu\text{V}/^\circ\text{C}$		
I_{IO}	Input offset current			25°C	1	60	pA		
I_{IB}	Input bias current			Full range	2	100			
				25°C	2	60			
				Full range	6	100			
V_{ICR}	Common-mode input voltage range	CMRR > 60 dB,	$R_S = 50 \Omega$	25°C	0	-0.3	V		
				Full range	0	-0.3			
V_{OH}	High-level output voltage	$I_{OH} = -1.3$ mA	$V_{IC} = 2.5$ V, $I_{OL} = 1.3$ mA	25°C	4.9		V		
				Full range	4.8				
		$I_{OH} = -4.2$ mA	$V_{IC} = 2.5$ V, $I_{OL} = 4.2$ mA	25°C	4.7				
				Full range	4.4				
V_{OL}	Low-level output voltage	$V_{IC} = 2.5$ V, $I_{OL} = 1.3$ mA	$V_{IC} = 2.5$ V, $I_{OL} = 4.2$ mA	25°C	0.1		V		
				Full range		0.2			
		$V_{IC} = 2.5$ V, $I_{OL} = 1.3$ mA	$V_{IC} = 2.5$ V, $I_{OL} = 4.2$ mA	25°C	0.21				
				Full range		0.6			
A_{VD}	Large-signal differential voltage amplification	$V_{IC} = 2.5$ V, $V_O = 1$ V to 4 V	$R_L = 10 \text{ k}\Omega$,	25°C	20	450	V/mV		
				Full range	13				
$r_i(d)$	Differential input resistance			25°C		10^{12}	Ω		
$C_{i(c)}$	Common-mode input capacitance	$f = 10$ kHz		25°C		8	pF		
Z_0	Closed-loop output impedance	$f = 100$ kHz, $A_V = 10$		25°C		20	Ω		
CMRR	Common-mode rejection ratio	$V_{IC} = 0$ to 3.7 V, $R_S = 50 \Omega$	$V_O = 3.7$ V,	25°C	60	96	dB		
				Full range	60	93			
k_{SVR}	Supply voltage rejection ratio ($\Delta V_{DD} / \Delta V_{IO}$)	$V_{DD} = 2.7$ V to 5 V, No load	$V_{IC} = V_{DD}/2$,	25°C	70	89	dB		
				Full range	70	84			
I_{DD}	Supply current (per channel)	$V_O = 1.5$ V,	No load	25°C	1	2	mA		
				Full range		2			
$I_{DD(SHDN)}$	Supply current in shutdown (per channel)			25°C	0.8	1.5	μA		
				Full range	1.3	2			
$V_{(ON)}$	Turnon voltage level	TLV2770 TLV2773 TLV2775	$A_V = 5$	25°C	2.59		V		
					2.47				
					2.48				
$V_{(OFF)}$	Turnoff voltage level	TLV2770 TLV2773 TLV2775	$A_V = 5$	25°C	2.41		V		
					2.32				
					2.29				

[†] Full range is 0°C to 70°C.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

operating characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLV277xC			UNIT
			MIN	TYP	MAX	
SR Slew rate at unity gain	$V_{O(PP)} = 1.5$ V, $C_L = 100$ pF, $R_L = 10$ k Ω	25°C	5	10.5		V/ μ s
		Full range	4.7	6		
V_n Equivalent input noise voltage	f = 1 kHz	25°C	17			nV/ $\sqrt{\text{Hz}}$
	f = 10 kHz	25°C	12			
$V_{N(PP)}$ Peak-to-peak equivalent input noise voltage	f = 0.1 Hz to 1 Hz	25°C	0.33			μ V
	f = 0.1 Hz to 10 Hz		0.86			
I_n Equivalent input noise current	f = 100 Hz	25°C	0.6			fA/ $\sqrt{\text{Hz}}$
THD + N Total harmonic distortion plus noise	$R_L = 600$ Ω , f = 1 kHz	A $V = 1$	0.005%			
		A $V = 10$	0.016%			
		A $V = 100$	0.095%			
Gain-bandwidth product	f = 10 kHz, $C_L = 100$ pF	$R_L = 600$ Ω ,	25°C	5.1		MHz
t_s Settling time	A $V = -1$, Step = 2 V, $R_L = 600$ Ω , $C_L = 100$ pF	0.1%	25°C	0.335		μ s
		0.01%	25°C	0.6		
ϕ_m Phase margin at unity gain	$R_L = 600$ Ω ,	$C_L = 100$ pF	25°C	46°		
			25°C	12		
$t_{(ON)}$ Amplifier turnon time	TLV2770	A $V = 5$, $R_L = \text{Open}$, Measured to 50% point	25°C	1.2		μ s
	TLV2773			2.4		
	TLV2775			1.9		
$t_{(OFF)}$ Amplifier turnoff time	TLV2770	A $V = 5$, $R_L = \text{Open}$, Measured to 50% point	25°C	335		ns
	TLV2773			444		
	TLV2775			345		

[†] Full range is 0°C to 70°C.

**TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

electrical characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xI			TLV277xAI			UNIT	
				MIN	TYP	MAX	MIN	TYP	MAX		
V_{IO}	Input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$ $V_{DD} = \pm 1.35$ V	25°C	0.44	2.5	0.44	1.6			mV	
			Full range	0.47	2.7	0.47	1.9				
	TLV2773/4/5		25°C	0.8	2.7	0.8	2.1				
			Full range	0.86	2.9	0.86	2.2				
α_{VIO}	Temperature coefficient of input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$	25°C to 125°C	2		2				$\mu\text{V}/^\circ\text{C}$	
I_{IO}	Input offset current		25°C	1	60	1	60			pA	
			Full range	2	125	2	125				
I_{IB}	Input bias current		25°C	2	60	2	60			pA	
			Full range	6	350	6	350				
V_{ICR}	Common-mode input voltage range	$\text{CMRR} > 70$ dB, $R_S = 50 \Omega$	25°C	0 to 1.4	-0.3 to 1.7	0 to 1.4	-0.3 to 1.7			V	
			Full range	0 to 1.4	-0.3 to 1.7	0 to 1.4	-0.3 to 1.7				
			$I_{OH} = -0.675$ mA	25°C	2.6	2.6				V	
			Full range	2.5		2.5					
V_{OH}	High-level output voltage	$I_{OH} = -2.2$ mA	25°C	2.4		2.4				V	
			Full range	2.1		2.1					
V_{OL}	Low-level output voltage	$V_{IC} = 1.35$ V, $I_{OL} = 0.675$ mA	25°C	0.1		0.1				V	
			Full range		0.2		0.2				
		$V_{IC} = 1.35$ V, $I_{OL} = 2.2$ mA	25°C	0.21		0.21					
			Full range		0.6		0.6				
A_{VD}	Large-signal differential voltage amplification	$V_{IC} = 1.35$ V, $R_L = 10 \text{ k}\Omega$, $V_O = 0.6$ V to 2.1 V	25°C	20	380	20	380			V/mV	
			Full range	13		13					
$r_{i(d)}$	Differential input resistance		25°C	10^{12}		10^{12}				Ω	
$C_{i(c)}$	Common-mode input capacitance	$f = 10$ kHz,	25°C	8		8				pF	
z_o	Closed-loop output impedance	$f = 100$ kHz, $A_V = 10$	25°C	25		25				Ω	
CMRR	Common-mode rejection ratio	$V_{IC} = 0$ to 1.5 V, $V_O = 1.5$ V, $R_S = 50 \Omega$	25°C	70	84	70	84			dB	
			Full range	70	82	70	82				
k_{SVR}	Supply voltage rejection ratio ($\Delta V_{DD} / \Delta V_{IO}$)	$V_{DD} = 2.7$ V to 5 V, $V_{IC} = V_{DD}/2$, No load	25°C	70	89	70	89			dB	
			Full range	70	84	70	84				
I_{DD}	Supply current (per channel)	$V_O = 1.5$ V, No load	25°C	1	2	1	2			mA	
			Full range		2		2				
$I_{DD(SHDN)}$	Supply current in shutdown (per channel)		25°C	0.8	1.5	0.8	1.5			μA	
			Full range	1.3	2	1.3	2				

[†] Full range is –40°C to 125°C.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

**electrical characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)
(continued)**

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xI			TLV277xAI			UNIT
				MIN	TYP	MAX	MIN	TYP	MAX	
$V_{(ON)}$	Turnon voltage level	TLV2770	$A_V = 5$	25°C	1.47		1.47			V
		TLV2773			1.43		1.43			
		TLV2775			1.40		1.4			
$V_{(OFF)}$	Turnoff voltage level	TLV2770	$A_V = 5$	25°C	1.27		1.27			V
		TLV2773			1.21		1.21			
		TLV2775			1.20		1.2			

† Full range is –40°C to 125°C.

operating characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xI			TLV277xAI			UNIT
				MIN	TYP	MAX	MIN	TYP	MAX	
SR	Slew rate at unity gain	$V_O(PP) = 0.8$ V, $C_L = 100$ pF, $R_L = 10$ kΩ	25°C	5	9		5	9		V/μs
			Full range	4.7	6		4.7	6		
V_n	Equivalent input noise voltage	f = 1 kHz	25°C	21		21				nV/√Hz
		f = 10 kHz	25°C	17		17				
$V_{N(PP)}$	Peak-to-peak equivalent input noise voltage	f = 0.1 Hz to 1 Hz	25°C	0.33		0.33				μV
		f = 0.1 Hz to 10 Hz	25°C	0.86		0.86				μV
I_n	Equivalent input noise current	f = 100 Hz	25°C	0.6		0.6				fA/√Hz
THD + N	Total harmonic distortion plus noise	$R_L = 600$ Ω, f = 1 kHz	$A_V = 1$	25°C	0.0085%		0.0085%			μs
			$A_V = 10$		0.025%		0.025%			
			$A_V = 100$		0.12%		0.12%			
	Gain-bandwidth product	f = 10 kHz, $C_L = 100$ pF	$R_L = 600$ Ω,	25°C	4.8		4.8			MHz
t_s	Settling time	$A_V = -1$, Step = 0.85 V to 1.85 V, $R_L = 600$ Ω, $C_L = 100$ pF	0.1%	25°C	0.186		0.186			μs
			0.01%	25°C	3.92		3.92			
ϕ_m	Phase margin at unity gain	$R_L = 600$ Ω, $C_L = 100$ pF	25°C	46°		46°				
	Gain margin		25°C	12		12				dB

† Full range is –40°C to 125°C.

TLV277x, TLV277xA**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT****OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

electrical characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xI			TLV277xAI			UNIT	
				MIN	TYP	MAX	MIN	TYP	MAX		
V_{IO}	Input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$, $V_{DD} = \pm 2.5$ V	25°C	0.36	2.5		0.36	1.6		mV	
			Full range	0.4	2.7		0.4	1.9			
	TLV2773/4/5		25°C	0.7	2.5		0.7	2.1			
			Full range	0.78	2.7		0.78	2.2			
α_{VIO}	Temperature coefficient of input offset voltage	$V_{IC} = 0$, $V_O = 0$, $R_S = 50 \Omega$, $V_{DD} = \pm 2.5$ V	25°C to 125°C	2			2			$\mu\text{V}/^\circ\text{C}$	
I_{IO}	Input offset current		25°C	1	60		1	60		pA	
			Full range	2	125		2	125			
	Input bias current		25°C	2	60		2	60			
			Full range	6	350		6	350			
V_{ICR}	Common-mode input voltage range	CMRR > 60 dB, $R_S = 50 \Omega$	25°C	0 to 3.7	-0.3 to 3.8		0 to 3.7	-0.3 to 3.8		V	
			Full range	0 to 3.7	-0.3 to 3.8		0 to 3.7	-0.3 to 3.8			
	High-level output voltage		25°C	4.9			4.9				
			Full range	4.8			4.8				
V_{OH}	$I_{OH} = -1.3$ mA		25°C	4.7			4.7			V	
			Full range	4.4			4.4				
	$I_{OH} = -4.2$ mA		25°C	0.1			0.1				
			Full range	0.2			0.2				
V_{OL}	Low-level output voltage	$V_{IC} = 2.5$ V, $I_{OL} = 1.3$ mA	25°C	0.21			0.21			V	
			Full range	0.6			0.6				
	Large-signal differential voltage amplification		25°C	20	450		20	450			
			Full range	13			13				
$r_{i(d)}$	Differential input resistance		25°C	10^{12}			10^{12}			Ω	
$C_{i(c)}$	Common-mode input capacitance	$f = 10$ kHz	25°C	8			8			pF	
z_0	Closed-loop output impedance	$f = 100$ kHz, $A_V = 10$	25°C	20			20			Ω	
CMRR	Common-mode rejection ratio	$V_{IC} = 0$ to 3.7 V, $V_O = 3.7$ V, $R_S = 50 \Omega$	25°C	60	96		60	96		dB	
			Full range	60	93		60	93			
k_{SVR}	Supply voltage rejection ratio ($\Delta V_{DD} / \Delta V_{IO}$)	$V_{DD} = 2.7$ V to 5 V, $V_{IC} = V_{DD}/2$, No load	25°C	70	89		70	89		dB	
			Full range	70	84		70	84			
I_{DD}	Supply current (per channel)	$V_O = 1.5$ V, No load	25°C	1	2		1	2		mA	
			Full range	2			2				
$I_{DD(SHDN)}$	Supply current shutdown (per channel)		25°C	0.8	1.5		0.8	1.5		μA	
			Full range	1.3	2		1.3	2			

[†] Full range is –40°C to 125°C.

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

**electrical characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)
(continued)**

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xI			TLV277xAI			UNIT
				MIN	TYP	MAX	MIN	TYP	MAX	
$V_{(ON)}$	Turnon voltage level	TLV2770	$A_V = 5$	25°C	2.59		2.59			V
		TLV2773			2.47		2.47			
		TLV2775			2.48		2.48			
$V_{(OFF)}$	Turnoff voltage level	TLV2770	$A_V = 5$	25°C	2.41		2.41			V
		TLV2773			2.32		2.32			
		TLV2775			2.29		2.29			

† Full range is –40°C to 125°C.

operating characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)

PARAMETER		TEST CONDITIONS	T_A^\dagger	TLV277xI			TLV277xAI			UNIT
				MIN	TYP	MAX	MIN	TYP	MAX	
SR	Slew rate at unity gain	$V_O(PP) = 1.5$ V, $C_L = 100$ pF, $R_L = 10$ kΩ	25°C	5	10.5		5	10.5		V/μs
			Full range	4.7	6		4.7	6		
V_n	Equivalent input noise voltage	f = 1 kHz	25°C	17		17				nV/√Hz
		f = 10 kHz	25°C	12		12				
$V_{N(PP)}$	Peak-to-peak equivalent input noise voltage	f = 0.1 Hz to 1 Hz	25°C	0.33		0.33				μV
		f = 0.1 Hz to 10 Hz	25°C	0.86		0.86				μV
I_n	Equivalent input noise current	f = 100 Hz	25°C	0.6		0.6				fA/√Hz
THD + N	Total harmonic distortion plus noise	$R_L = 600$ Ω, f = 1 kHz	$A_V = 1$	25°C	0.005%		0.005%			
			$A_V = 10$		0.016%		0.016%			
			$A_V = 100$		0.095%		0.095%			
Gain-bandwidth product		f = 10 kHz, $C_L = 100$ pF	$R_L = 600$ Ω,	25°C	5.1		5.1			MHz
t_s	Settling time	$A_V = -1$, Step = 1.5 V to 3.5 V, $R_L = 600$ Ω, $C_L = 100$ pF	0.1%	25°C	0.134		0.134			μs
			0.01%	25°C	1.97		1.97			
ϕ_m	Phase margin at unity gain	$R_L = 600$ Ω, $C_L = 100$ pF	25°C	46°		46°				
			25°C	12		12				
t(ON)	Amplifier turnon time	$A_V = 5$, $R_L = \text{Open}$, Measured to 50% point	25°C	1.2		1.2				μs
				2.4		2.4				
				1.9		1.9				
t(OFF)	Amplifier turnoff time	$A_V = 5$, $R_L = \text{Open}$, Measured to 50% point	25°C	335		335				ns
				444		444				
				345		345				

† Full range is –40°C to 125°C.

**TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

electrical characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLV2772Q TLV2772M			TLV2772AQ TLV2772AM			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{IO} Input offset voltage	$V_{DD} = \pm 1.35$ V, $V_{IC} = 0$, $R_S = 50\Omega$	25°C	0.44	2.5		0.44	1.6		mV
		Full range	0.47	2.7		0.47	1.9		
αV_{IO} Temperature coefficient of input offset voltage	$V_O = 0$,	25°C to 125°C		2			2		$\mu V/{^\circ C}$
		25°C	1	60		1	60		
I_{IO} Input offset current		Full range	2	125		2	125		pA
		25°C	2	60		2	60		
I_{IB} Input bias current		Full range	6	350		6	350		pA
		25°C	0 to 1.4	-0.3 to 1.7		0 to 1.4	-0.3 to 1.7		
V_{ICR} Common-mode input voltage range	$CMRR > 60$ dB, $R_S = 50\Omega$	Full range	0 to 1.4	-0.3 to 1.7		0 to 1.4	-0.3 to 1.7		V
		25°C	0 to 1.4	-0.3 to 1.7		0 to 1.4	-0.3 to 1.7		
V_{OH} High-level output voltage	$I_{OH} = -0.675$ mA	25°C	2.6		2.6				V
		Full range	2.45		2.45				
V_{OL} Low-level output voltage	$V_{IC} = 1.35$ V, $I_{OL} = 0.675$ mA	25°C	2.4		2.4				V
		Full range	2.1		2.1				
V_{OL} Low-level output voltage	$V_{IC} = 1.35$ V, $I_{OL} = 2.2$ mA	25°C	0.1		0.1				V
		Full range	0.2		0.2				
A_{VD} Large-signal differential voltage amplification	$V_{IC} = 1.35$ V, $V_O = 0.6$ V to 2.1 V	25°C	0.21		0.21				V/mV
		Full range	0.6		0.6				
$r_{i(d)}$ Differential input resistance		25°C	10^{12}			10^{12}			Ω
$C_{i(c)}$ Common-mode input capacitance	$f = 10$ kHz,	25°C	8		8				pF
z_o Closed-loop output impedance	$f = 100$ kHz, $A_V = 10$	25°C	25		25				Ω
$CMRR$ Common-mode rejection ratio	$V_{IC} = V_{ICR}$ (min), $V_O = 1.5$ V, $R_S = 50\Omega$	25°C	60	84		60	84		dB
		Full range	60	82		60	82		
k_{SVR} Supply voltage rejection ratio ($\Delta V_{DD} / \Delta V_{IO}$)	$V_{DD} = 2.7$ V to 5 V, $V_{IC} = V_{DD}/2$, No load	25°C	70	89		70	89		dB
		Full range	70	84		70	84		
I_{DD} Supply current (per channel)	$V_O = 1.5$ V, No load	25°C	1	2		1	2		mA
		Full range		2			2		

† Full range is $-40^\circ C$ to $125^\circ C$ for Q level part, $-55^\circ C$ to $125^\circ C$ for M level part.

‡ Referenced to 1.35 V



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

operating characteristics at specified free-air temperature, $V_{DD} = 2.7$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLV2772Q TLV2772M			TLV2772AQ TLV2772AM			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
SR	Slew rate at unity gain $V_O(PP) = 0.8$ V, $C_L = 100$ pF, $R_L = 10$ k Ω	25°C	5	9		5	9		V/ μ s
		Full range	4.7	6		4.7	6		
V_n	Equivalent input noise voltage $f = 1$ kHz	25°C	21			21			nV/ $\sqrt{\text{Hz}}$
		25°C	17			17			
$V_N(PP)$	Peak-to-peak equivalent input noise voltage $f = 0.1$ Hz to 1 Hz	25°C	0.33			0.33			μ V
		25°C	0.86			0.86			
I_n	Equivalent input noise current $f = 100$ Hz	25°C	0.6			0.6			fA/ $\sqrt{\text{Hz}}$
THD + N	Total harmonic distortion plus noise $R_L = 600$ Ω , $f = 1$ kHz	$A_V = 1$ $A_V = 10$ $A_V = 100$	25°C	0.0085%		0.0085%			
				0.025%		0.025%			
				0.12%		0.12%			
Gain-bandwidth product		$f = 10$ kHz, $C_L = 100$ pF	$R_L = 600$ Ω ,	25°C	4.8		4.8		MHz
t_s	Settling time	$A_V = -1$, Step = 0.85 V to 1.85 V, $R_L = 600$ Ω , $C_L = 100$ pF	0.1%	25°C	0.186		0.186		μ s
			0.01%	25°C	3.92		3.92		
ϕ_m	Phase margin at unity gain	$R_L = 600$ Ω ,	$C_L = 100$ pF	25°C	46°		46°		
	Gain margin			25°C	12		12		

[†] Full range is -40°C to 125°C for Q level part, -55°C to 125°C for M level part.



**TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

electrical characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLV2772Q TLV2772M			TLV2772AQ TLV2772AM			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{IO} Input offset voltage	$V_{DD} = \pm 2.5$ V, $V_{IC} = 0$, $R_S = 50\Omega$	25°C	0.36	2.5		0.36	1.6		mV
		Full range	0.4	2.7		0.4	1.9		
αV_{IO} Temperature coefficient of input offset voltage	$V_{DD} = \pm 2.5$ V, $V_{IC} = 0$, $R_S = 50\Omega$	25°C to 125°C		2			2		$\mu V/^\circ C$
		25°C	1	60		1	60		
I_{IO} Input offset current	$V_{DD} = \pm 2.5$ V, $V_{IC} = 0$, $R_S = 50\Omega$	Full range	2	125		2	125		pA
		25°C	2	60		2	60		
I_{IB} Input bias current	$V_{DD} = \pm 2.5$ V, $V_{IC} = 0$, $R_S = 50\Omega$	Full range	6	350		6	350		pA
		25°C	0 to 3.7	-0.3 to 3.8		0 to 3.7	-0.3 to 3.8		
V_{ICR} Common-mode input voltage range	$CMRR > 60$ dB, $R_S = 50\Omega$	Full range	0 to 3.7	-0.3 to 3.8		0 to 3.7	-0.3 to 3.8		V
		25°C	0 to 3.7	-0.3 to 3.8		0 to 3.7	-0.3 to 3.8		
V_{OH} High-level output voltage	$I_{OH} = -1.3$ mA	25°C	4.9			4.9			V
		Full range	4.8			4.8			
	$I_{OH} = -4.2$ mA	25°C	4.7			4.7			
		Full range	4.4			4.4			
V_{OL} Low-level output voltage	$V_{IC} = 2.5$ V, $I_{OL} = 1.3$ mA	25°C	0.1			0.1			V
		Full range		0.2			0.2		
	$V_{IC} = 2.5$ V, $I_{OL} = 4.2$ mA	25°C	0.21			0.21			
		Full range		0.6			0.6		
A_{VD} Large-signal differential voltage amplification	$V_{IC} = 2.5$ V, $V_O = 1$ V to 4 V	25°C	20	450		20	450		V/mV
		Full range	13			13			
$r_{i(d)}$ Differential input resistance		25°C	10^{12}			10^{12}			Ω
$C_{i(c)}$ Common-mode input capacitance	$f = 10$ kHz,	25°C		8			8		pF
z_o Closed-loop output impedance	$f = 100$ kHz, $A_V = 10$	25°C		20			20		Ω
$CMRR$ Common-mode rejection ratio	$V_{IC} = V_{ICR}$ (min), $R_S = 50\Omega$	25°C	60	96		60	96		dB
		Full range	60	93		60	93		
k_{SVR} Supply voltage rejection ratio ($\Delta V_{DD} / \Delta V_{IO}$)	$V_{DD} = 2.7$ V to 5 V, No load	25°C	70	89		70	89		dB
		Full range	70	84		70	84		
I_{DD} Supply current (per channel)	$V_O = 1.5$ V, No load	25°C	1	2		1	2		mA
		Full range		2			2		

[†] Full range is -40°C to 125°C for Q level part, -55°C to 125°C for M level part.

[‡] Referenced to 2.5 V



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TLV277x, TLV277xA
**FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**
SLOS209F – JANUARY 1998 – REVISED MARCH 2001

operating characteristics at specified free-air temperature, $V_{DD} = 5$ V (unless otherwise noted)

PARAMETER	TEST CONDITIONS	T_A^\dagger	TLV2772Q TLV2772M			TLV2772AQ TLV2772AM			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
SR	Slew rate at unity gain $V_O(PP) = 1.5$ V, $C_L = 100$ pF, $R_L = 10$ k Ω	25°C	5	10.5		5	10.5		V/ μ s
		Full range	4.7	6		4.7	6		
V_n	Equivalent input noise voltage $f = 1$ kHz	25°C		17			17		nV/ $\sqrt{\text{Hz}}$
		25°C		12			12		
$V_N(PP)$	Peak-to-peak equivalent input noise voltage $f = 0.1$ Hz to 1 Hz	25°C		0.33			0.33		μ V
		25°C		0.86			0.86		
I_n	Equivalent input noise current	$f = 100$ Hz	25°C		0.6		0.6		fA/ $\sqrt{\text{Hz}}$
THD + N	Total harmonic distortion plus noise $R_L = 600$ Ω , $f = 1$ kHz	$A_V = 1$	25°C		0.005%		0.005%		
		$A_V = 10$			0.016%		0.016%		
		$A_V = 100$			0.095%		0.095%		
	Gain-bandwidth product	$f = 10$ kHz, $C_L = 100$ pF	$R_L = 600$ Ω ,	25°C		5.1		5.1	MHz
t_s	Settling time $A_V = -1$, Step = 1.5 V to 3.5 V, $R_L = 600$ Ω , $C_L = 100$ pF	0.1%	25°C		0.134		0.134		μ s
		0.01%	25°C		1.97		1.97		
ϕ_m	Phase margin at unity gain $R_L = 600$ Ω , $C_L = 100$ pF		25°C		46°		46°		
			25°C		12		12		
	Gain margin								dB

[†] Full range is -40°C to 125°C for Q level part, -55°C to 125°C for M level part.

**TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN**

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS

Table of Graphs

			FIGURE
V _{IO}	Input offset voltage	Distribution vs Common-mode input voltage Distribution	1,2 3,4 5,6
I _{IB} /I _{IO}	Input bias and input offset currents	vs Free-air temperature	7
V _{OH}	High-level output voltage	vs High-level output current	8,9
V _{OL}	Low-level output voltage	vs Low-level output current	10,11
V _{O(PP)}	Maximum peak-to-peak output voltage	vs Frequency	12,13
I _{OS}	Short-circuit output current	vs Supply voltage vs Free-air temperature	14 15
V _O	Output voltage	vs Differential input voltage	16
A _{VD}	Large-signal differential voltage amplification and phase margin	vs Frequency	17,18
A _{VD}	Differential voltage amplification	vs Load resistance vs Free-air temperature	19 20,21
Z _O	Output impedance	vs Frequency	22,23
C _{MRR}	Common-mode rejection ratio	vs Frequency vs Free-air temperature	24 25
k _{SVR}	Supply-voltage rejection ratio	vs Frequency	26,27
I _{DD}	Supply current (per channel)	vs Supply voltage	28
S _R	Slew rate	vs Load capacitance vs Free-air temperature	29 30
V _O	Voltage-follower small-signal pulse response		31,32
V _O	Voltage-follower large-signal pulse response		33,34
V _O	Inverting small-signal pulse response		35,36
V _O	Inverting large-signal pulse response		37,38
V _n	Equivalent input noise voltage	vs Frequency	39,40
	Noise voltage (referred to input)	Over a 10-second period	41
THD + N	Total harmonic distortion plus noise	vs Frequency	42,43
	Gain-bandwidth product	vs Supply voltage	44
B ₁	Unity-gain bandwidth	vs Load capacitance	45
φ _m	Phase margin	vs Load capacitance	46
	Gain margin	vs Load capacitance	47
	Amplifier with shutdown pulse turnon/off characteristics		48 – 50
	Supply current with shutdown pulse turnon/off characteristics		51 – 53
	Shutdown supply current	vs Free-air temperature	54
	Shutdown forward/reverse isolation	vs Frequency	55, 56

TYPICAL CHARACTERISTICS

**DISTRIBUTION OF TLV2772
 INPUT OFFSET VOLTAGE**




Figure 1

**DISTRIBUTION OF TLV2772
 INPUT OFFSET VOLTAGE**




Figure 2

**INPUT OFFSET VOLTAGE
 vs
 COMMON-MODE INPUT VOLTAGE**




Figure 3

**INPUT OFFSET VOLTAGE
 vs
 COMMON-MODE INPUT VOLTAGE**




Figure 4

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS




Figure 5




Figure 6




Figure 7




Figure 8

TYPICAL CHARACTERISTICS




Figure 9




Figure 10




Figure 11




Figure 12

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS

**MAXIMUM PEAK-TO-PEAK OUTPUT VOLTAGE
vs
FREQUENCY**




Figure 13

**SHORT-CIRCUIT OUTPUT CURRENT
vs
SUPPLY VOLTAGE**




Figure 14

**SHORT-CIRCUIT OUTPUT CURRENT
vs
FREE-AIR TEMPERATURE**




Figure 15

**OUTPUT VOLTAGE
vs
DIFFERENTIAL INPUT VOLTAGE**




Figure 16

TYPICAL CHARACTERISTICS

**LARGE-SIGNAL DIFFERENTIAL VOLTAGE AMPLIFICATION
 AND PHASE MARGIN**
 vs
 FREQUENCY




Figure 17

**LARGE-SIGNAL DIFFERENTIAL VOLTAGE AMPLIFICATION
 AND PHASE MARGIN**
 vs
 FREQUENCY




Figure 18

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS




Figure 19




Figure 20




Figure 21




Figure 22

TYPICAL CHARACTERISTICS




Figure 23




Figure 24




Figure 25




Figure 26

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS




Figure 27




Figure 28




Figure 29




Figure 30

TYPICAL CHARACTERISTICS

**VOLTAGE-FOLLOWER
 SMALL-SIGNAL PULSE RESPONSE**




Figure 31

**VOLTAGE-FOLLOWER
 SMALL-SIGNAL PULSE RESPONSE**




Figure 32

**VOLTAGE-FOLLOWER
 LARGE-SIGNAL PULSE RESPONSE**




Figure 33

**VOLTAGE-FOLLOWER
 LARGE-SIGNAL PULSE RESPONSE**




Figure 34

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS




Figure 35




Figure 36




Figure 37




Figure 38

TYPICAL CHARACTERISTICS

**EQUIVALENT INPUT NOISE VOLTAGE
 VS
 FREQUENCY**




Figure 39

**EQUIVALENT INPUT NOISE VOLTAGE
 VS
 FREQUENCY**




Figure 40

**NOISE VOLTAGE
 OVER A 10 SECOND PERIOD**




Figure 41

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS




Figure 42




Figure 43




Figure 44




Figure 45

TYPICAL CHARACTERISTICS




Figure 46




Figure 47




Figure 48




Figure 49

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

TYPICAL CHARACTERISTICS




Figure 50




Figure 51




Figure 52




Figure 53

TYPICAL CHARACTERISTICS




Figure 54




Figure 55




Figure 56

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

PARAMETER MEASUREMENT INFORMATION




Figure 57

driving a capacitive load

When the amplifier is configured in this manner, capacitive loading directly on the output will decrease the device's phase margin leading to high frequency ringing or oscillations. Therefore, for capacitive loads of greater than 10 pF, it is recommended that a resistor be placed in series (R_{NULL}) with the output of the amplifier, as shown in Figure 58. A minimum value of 20 Ω should work well for most applications.




Figure 58. Driving a Capacitive Load

APPLICATION INFORMATION

offset voltage

The output offset voltage, (V_{OO}) is the sum of the input offset voltage (V_{IO}) and both input bias currents (I_{IB}) times the corresponding gains. The following schematic and formula can be used to calculate the output offset voltage:




Figure 59. Output Offset Voltage Model

general configurations

When receiving low-level signals, limiting the bandwidth of the incoming signals into the system is often required. The simplest way to accomplish this is to place an RC filter at the noninverting terminal of the amplifier (see Figure 60).




Figure 60. Single-Pole Low-Pass Filter

If even more attenuation is needed, a multiple pole filter is required. The Sallen-Key filter can be used for this task. For best results, the amplifier should have a bandwidth that is 8 to 10 times the filter frequency bandwidth. Failure to do this can result in phase shift of the amplifier.




Figure 61. 2-Pole Low-Pass Sallen-Key Filter

TLV277x, TLV277xA FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

APPLICATION INFORMATION

using the TLV2772 as an accelerometer interface

The schematic, shown in Figure 62, shows the ACH04-08-05 interfaced to the TLV1544 10-bit analog-to-digital converter (ADC).

The ACH04-08-05 is a shock sensor designed to convert mechanical acceleration into electrical signals. The sensor contains three piezoelectric sensing elements oriented to simultaneously measure acceleration in three orthogonal, linear axes (x, y, z). The operating frequency is 0.5 Hz to 5 kHz. The output is buffered with an internal JFET and has a typical output voltage of 1.80 mV/g for the x and y axis and 1.35 mV/g for the z axis.

Amplification and frequency shaping of the shock sensor output is done by the TLV2772 rail-to-rail operational amplifier. The TLV2772 is ideal for this application as it offers high input impedance, good slew rate, and excellent dc precision. The rail-to-rail output swing and high output drive are perfect for driving the analog input of the TLV1544 ADC.




Figure 62. Accelerometer Interface Schematic

The sensor signal must be amplified and frequency-shaped to provide a signal the ADC can properly convert into the digital domain. Figure 62 shows the topology used in this application for one axis of the sensor. This system is powered from a single 3-V supply. Configuring the TLV431 with a 2.2-kΩ resistor produces a reference voltage of 1.23 V. This voltage is used to bias the operational amplifier and the internal JFETs in the shock sensor.

APPLICATION INFORMATION

gain calculation

Since the TLV2772 is capable of rail-to-rail output using a 3-V supply, $V_O = 0$ (min) to 3 V (max). With no signal from the sensor, nominal V_O = reference voltage = 1.23 V. Therefore, the maximum negative swing from nominal is $0\text{ V} - 1.23\text{ V} = -1.23\text{ V}$ and the maximum positive swing is $3\text{ V} - 1.23\text{ V} = 1.77\text{ V}$. By modeling the shock sensor as a low impedance voltage source with output of 2.25 mV/g (max) in the x and y axis and 1.70 mV/g (max) in the z axis, the gain of the circuit is calculated by equation 1.

$$\text{Gain} = \frac{\text{Output Swing}}{\text{Sensor Signal} \times \text{Acceleration}} \quad (1)$$

To avoid saturation of the operational amplifier, the gain calculations are based on the maximum negative swing of -1.23 V and the maximum sensor output of 2.25 mV/g (x and y axis) and 1.70 mV/g (z axis).

$$\text{Gain (x, y)} = \frac{-1.23\text{ V}}{2.25\text{ mV/g} \times -50\text{ g}} = 10.9 \quad (2)$$

and

$$\text{Gain (z)} = \frac{-1.23\text{ V}}{1.70\text{ mV/g} \times -50\text{ g}} = 14.5 \quad (3)$$

By selecting $R_3 = 10\text{ k}\Omega$ and $R_4 = 100\text{ k}\Omega$, in the x and y channels, a gain of 11 is realized. By selecting $R_3 = 7.5\text{ k}\Omega$ and $R_4 = 100\text{ k}\Omega$, in the z channel, a gain of 14.3 is realized. The schematic shows the configuration for either the x- or y-axis.

bandwidth calculation

To calculate the component values for the frequency shaping characteristics of the signal conditioning circuit, 1 Hz and 500 Hz are selected as the minimum required 3-dB bandwidth.

To minimize the value of the input capacitor (C_1) required to set the lower cutoff frequency requires a large value resistor for R_2 is required. A 1-M Ω resistor is used in this example. To set the lower cutoff frequency, the required capacitor value for C_1 is:

$$C_1 = \frac{1}{2\pi f_{\text{LOW}} R_2} = 0.159\text{ }\mu\text{F} \quad (4)$$

Using a value of 0.22 μF , a more common value of capacitor, the lower cutoff frequency is 0.724 Hz.

To minimize the phase shift in the feedback loop caused by the input capacitance of the TLV2772, it is best to minimize the value of the feedback resistor R_4 . However, to reduce the required capacitance in the feedback loop a large value for R_4 is required. Therefore, a compromise for the value of R_4 must be made. In this circuit, a value of 100 $\text{k}\Omega$ has been selected. To set the upper cutoff frequency, the required capacitor value for C_2 is:

$$C_2 = \frac{1}{2\pi f_{\text{HIGH}} R_4} = 3.18\text{ }\mu\text{F} \quad (5)$$

Using a 2.2-nF capacitor, the upper cutoff frequency is 724 Hz.

R_5 and C_3 also cause the signal response to roll off. Therefore, it is beneficial to design this roll-off point to begin at the upper cutoff frequency. Assuming a value of 1 $\text{k}\Omega$ for R_5 , the value for C_3 is calculated to be 0.22 μF .

APPLICATION INFORMATION

circuit layout considerations

To achieve the levels of high performance of the TLV277x, follow proper printed-circuit board design techniques. A general set of guidelines is given in the following.

- **Ground planes**—It is highly recommended that a ground plane be used on the board to provide all components with a low inductive ground connection. However, in the areas of the amplifier inputs and output, the ground plane can be removed to minimize the stray capacitance.
- **Proper power supply decoupling**—Use a 6.8- μ F tantalum capacitor in parallel with a 0.1- μ F ceramic capacitor on each supply terminal. It may be possible to share the tantalum among several amplifiers depending on the application, but a 0.1- μ F ceramic capacitor should always be used on the supply terminal of every amplifier. In addition, the 0.1- μ F capacitor should be placed as close as possible to the supply terminal. As this distance increases, the inductance in the connecting trace makes the capacitor less effective. The designer should strive for distances of less than 0.1 inches between the device power terminals and the ceramic capacitors.
- **Sockets**—Sockets can be used but are not recommended. The additional lead inductance in the socket pins will often lead to stability problems. Surface-mount packages soldered directly to the printed-circuit board is the best implementation.
- **Short trace runs/compact part placements**—Optimum high performance is achieved when stray series inductance has been minimized. To realize this, the circuit layout should be made as compact as possible, thereby minimizing the length of all trace runs. Particular attention should be paid to the inverting input of the amplifier. Its length should be kept as short as possible. This will help to minimize stray capacitance at the input of the amplifier.
- **Surface-mount passive components**—Using surface-mount passive components is recommended for high performance amplifier circuits for several reasons. First, because of the extremely low lead inductance of surface-mount components, the problem with stray series inductance is greatly reduced. Second, the small size of surface-mount components naturally leads to a more compact layout thereby minimizing both stray inductance and capacitance. If leaded components are used, it is recommended that the lead lengths be kept as short as possible.



APPLICATION INFORMATION

general power dissipation considerations

For a given θ_{JA} , the maximum power dissipation is shown in Figure 63 and is calculated by the following formula:

$$P_D = \left(\frac{T_{MAX} - T_A}{\theta_{JA}} \right)$$

Where:

P_D = Maximum power dissipation of TLV277x IC (watts)


T_{MAX} = Absolute maximum junction temperature (150°C)

T_A = Free-ambient air temperature ($^{\circ}\text{C}$)

θ_{JA} = $\theta_{JC} + \theta_{CA}$

θ_{JC} = Thermal coefficient from junction to case

θ_{CA} = Thermal coefficient from case to ambient air ($^{\circ}\text{C/W}$)



NOTE A: Results are with no air flow and using JEDEC Standard Low-K test PCB.

Figure 63. Maximum Power Dissipation vs Free-Air Temperature

TLV277x, TLV277xA

FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT

OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

APPLICATION INFORMATION

shutdown function

Three members of the TLV277x family (TLV2770/3/5) have a shutdown terminal for conserving battery life in portable applications. When the shutdown terminal is tied low, the supply current is reduced to $0.8 \mu\text{A}/\text{channel}$, the amplifier is disabled, and the outputs are placed in a high impedance mode. To enable the amplifier, the shutdown terminal can either be left floating or pulled high. When the shutdown terminal is left floating, care needs to be taken to ensure that parasitic leakage current at the shutdown terminal does not inadvertently place the operational amplifier into shutdown. The shutdown terminal threshold is always referenced to $V_{DD}/2$. Therefore, when operating the device with split supply voltages (e.g. $\pm 2.5 \text{ V}$), the shutdown terminal needs to be pulled to V_{DD-} (not GND) to disable the operational amplifier.

The amplifier's output with a shutdown pulse is shown in Figures 48, 49, and 50. The amplifier is powered with a single 5-V supply and configured as a noninverting configuration with a gain of 5. The amplifier turnon and turnoff times are measured from the 50% point of the shutdown pulse to the 50% point of the output waveform. The times for the single, dual, and quad are listed in the data tables. The *bump* on the rising edge of the TLV2770 output waveform is due to the start-up circuit on the bias generator. For the dual and quad (TLV2773/5), this *bump* is attributed to the bias generator's start-up circuit as well as the crosstalk between the other channel(s), which are in shutdown.

Figures 55 and 56 show the amplifier's forward and reverse isolation in shutdown. The operational amplifier is powered by $\pm 1.35\text{-V}$ supplies and configured as a voltage follower ($A_V = 1$). The isolation performance is plotted across frequency for both 0.1 V_{PP} and 2.7 V_{PP} input signals. During normal operation, the amplifier would not be able to handle a 2.7-V_{PP} input signal with a supply voltage of $\pm 1.35 \text{ V}$ since it exceeds the common-mode input voltage range (V_{ICR}). However, this curve illustrates that the amplifier remains in shutdown even under a worst case scenario.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265


APPLICATION INFORMATION

macromodel information

Macromodel information provided was derived using Microsim *Parts™* Release 8, the model generation software used with Microsim *PSpice™*. The Boyle macromodel (see Note 4) and subcircuit in Figure 64 are generated using the TLV2772 typical electrical and operating characteristics at $T_A = 25^\circ\text{C}$. Using this information, output simulations of the following key parameters can be generated to a tolerance of 20% (in most cases):

- Maximum positive output voltage swing
- Maximum negative output voltage swing
- Slew rate
- Quiescent power dissipation
- Input bias current
- Open-loop voltage amplification
- Unity-gain frequency
- Common-mode rejection ratio
- Phase margin
- DC output resistance
- AC output resistance
- Short-circuit output current limit

NOTE 4: G. R. Boyle, B. M. Cohn, D. O. Pederson, and J. E. Solomon, "Macromodeling of Integrated Circuit Operational Amplifiers", *IEEE Journal of Solid-State Circuits*, SC-9, 353 (1974).



* TLV2772 operational amplifier macromodel subcircuit
 * created using Parts release 8.0 on 12/12/97 at 10:08

* Parts is a MicroSim product.

* connections: noninverting input

* | inverting input

* | positive power supply

* | negative power supply

* | output

.subckt TLV2772

c1	11	12	2.8868E-12
c2	6	7	10.000E-12
css	10	99	2.6302E-12
dc	5	53	dy
de	54	5	dy
dln	92	90	dx
dp	4	3	dx
egnd	99	0	poly(2) (3,0) (4,0) 0 .5 .5
fb	7	99	poly(5) vb vc ve vlp vln 0 15.513E6 -1E3 1E3 16E6 -16E6
ga	6	0	11 12 188.50E-6
gcm	0	6	10 99 9.4472E-9

iss	3	10	dc	145.50E-6
hlim	90	0	vlim	1K
j1	11	2		10 jx1
j2	12	1		10 jx2
r2	6	9		100.00E3
rd1	4	11		5.3052E3
rd2	4	12		5.3052E3
ro1	8	5		17.140
ro2	7	99		17.140
rp	3	4		4.5455E3
rss	10	99		1.3746E6
vb	9	0		dc 0
vc	3	53		dc .82001
ve	54	4		dc .82001
vlim	7	8		dc 0
vlp	91	0		dc 47
vln	0	92		dc 47
.model	dx			D(Is=800.00E-18)
.model	dy			D(Is=800.00E-18 Rs=1m Cjo=10p)
.model	jx1			PJF(Is=2.2500E-12 Beta=244.20E-6 + Vto=-.99765)
.model	jx2			PJF(Is=1.7500E-12 Beta=244.20E-6 + Vto=-1.002350)
.ends				

*\$

Figure 64. Boyle Macromodel and Subcircuit

PSpice and *Parts* are trademarks of MicroSim Corporation.

TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN


SLOS209F – JANUARY 1998 – REVISED MARCH 2001

MECHANICAL INFORMATION

D (R-PDSO-G)**

14 PIN SHOWN

PLASTIC SMALL-OUTLINE PACKAGE




- NOTES:
- A. All linear dimensions are in inches (millimeters).
 - B. This drawing is subject to change without notice.
 - C. Body dimensions do not include mold flash or protrusion, not to exceed 0.006 (0,15).
 - D. Falls within JEDEC MS-012

MECHANICAL INFORMATION

DBV (R-PDSO-G5)

PLASTIC SMALL-OUTLINE PACKAGE



- NOTES: A. All linear dimensions are in millimeters.
 B. This drawing is subject to change without notice.
 C. Body dimensions include mold flash or protrusion.


TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

MECHANICAL INFORMATION

DBV (R-PDSO-G6)

PLASTIC SMALL-OUTLINE PACKAGE




4073253-5/B 10/97

- NOTES: A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions include mold flash or protrusion.

MECHANICAL INFORMATION

DGK (R-PDSO-G8)

PLASTIC SMALL-OUTLINE PACKAGE



- NOTES:
- All linear dimensions are in millimeters.
 - This drawing is subject to change without notice.
 - Body dimensions do not include mold flash or protrusion.


TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

MECHANICAL INFORMATION

DGS (S-PDSO-G10)

PLASTIC SMALL-OUTLINE PACKAGE




- NOTES: A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions do not include mold flash or protrusion.

MECHANICAL INFORMATION

FK (S-CQCC-N**)

28 TERMINAL SHOWN

LEADLESS CERAMIC CHIP CARRIER



- NOTES: A. All linear dimensions are in inches (millimeters).
 B. This drawing is subject to change without notice.
 C. This package can be hermetically sealed with a metal lid.
 D. The terminals are gold plated.
 E. Falls within JEDEC MS-004


TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

MECHANICAL INFORMATION

JG (R-GDIP-T8)

CERAMIC DUAL-IN-LINE PACKAGE




- NOTES:
- A. All linear dimensions are in inches (millimeters).
 - B. This drawing is subject to change without notice.
 - C. This package can be hermetically sealed with a ceramic lid using glass frit.
 - D. Index point is provided on cap for terminal identification on press ceramic glass frit seal.
 - E. Falls within MIL-STD-1835 GDIP1-T8

MECHANICAL INFORMATION

N (R-PDIP-T**)

16 PIN SHOWN

PLASTIC DUAL-IN-LINE PACKAGE



- NOTES:
- All linear dimensions are in inches (millimeters).
 - This drawing is subject to change without notice.
 - Falls within JEDEC MS-001 (20 pin package is shorter than MS-001.)


TLV277x, TLV277xA
FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT
OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

MECHANICAL INFORMATION

P (R-PDIP-T8)

PLASTIC DUAL-IN-LINE PACKAGE



4040082/B 03/95


- NOTES:
- A. All linear dimensions are in inches (millimeters).
 - B. This drawing is subject to change without notice.
 - C. Falls within JEDEC MS-001

MECHANICAL INFORMATION

PW (R-PDSO-G**)

PLASTIC SMALL-OUTLINE PACKAGE

14 PIN SHOWN



- NOTES: A. All linear dimensions are in millimeters.
 B. This drawing is subject to change without notice.
 C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.
 D. Falls within JEDEC MO-153

TLV277x, TLV277xA

FAMILY OF 2.7-V HIGH-SLEW-RATE RAIL-TO-RAIL OUTPUT


OPERATIONAL AMPLIFIERS WITH SHUTDOWN

SLOS209F – JANUARY 1998 – REVISED MARCH 2001

MECHANICAL INFORMATION

U (S-GDFP-F10)


CERAMIC DUAL FLATPACK



- NOTES:
- A. All linear dimensions are in inches (millimeters).
 - B. This drawing is subject to change without notice.
 - C. This package can be hermetically sealed with a ceramic lid using glass frit.
 - D. Index point is provided on cap for terminal identification only.
 - E. Falls within MIL STD 1835 GDFFP1-F10 and JEDEC MO-092AA

JG (R-GDIP-T8)


CERAMIC DUAL-IN-LINE



- NOTES: A. All linear dimensions are in inches (millimeters).
 B. This drawing is subject to change without notice.
 C. This package can be hermetically sealed with a ceramic lid using glass frit.
 D. Index point is provided on cap for terminal identification.
 E. Falls within MIL STD 1835 GDIP1-T8

U (S-GDFP-F10)

CERAMIC DUAL FLATPACK




- NOTES:
- All linear dimensions are in inches (millimeters).
 - This drawing is subject to change without notice.
 - This package can be hermetically sealed with a ceramic lid using glass frit.
 - Index point is provided on cap for terminal identification only.
 - Falls within MIL STD 1835 GDFP1-F10 and JEDEC MO-092AA

FK (S-CQCC-N**)

LEADLESS CERAMIC CHIP CARRIER

28 TERMINAL SHOWN



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

C. This package can be hermetically sealed with a metal lid.


D. The terminals are gold plated.

E. Falls within JEDEC MS-004

4040140/D 10/96

P (R-PDIP-T8)

PLASTIC DUAL-IN-LINE



- NOTES:
- All linear dimensions are in inches (millimeters).
 - This drawing is subject to change without notice.
 - Falls within JEDEC MS-001

For the latest package information, go to http://www.ti.com/sc/docs/package/pkg_info.htm


MECHANICAL

MPDI002C – JANUARY 1995 – REVISED DECEMBER 20002

N (R-PDIP-T**)

16 PINS SHOWN

PLASTIC DUAL-IN-LINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).


B. This drawing is subject to change without notice.

C. Falls within JEDEC MS-001, except 18 and 20 pin minimum body length (Dim A).

D. The 20 pin end lead shoulder width is a vendor option, either half or full width.

DBV (R-PDSO-G5)


PLASTIC SMALL-OUTLINE



- NOTES:
- All linear dimensions are in millimeters.
 - This drawing is subject to change without notice.
 - Body dimensions do not include mold flash or protrusion.
 - Falls within JEDEC MO-178

DGK (R-PDSO-G8)


PLASTIC SMALL-OUTLINE PACKAGE



- NOTES: A. All linear dimensions are in millimeters.
 B. This drawing is subject to change without notice.
 C. Body dimensions do not include mold flash or protrusion.
 D. Falls within JEDEC MO-187

DGS (S-PDSO-G10)

PLASTIC SMALL-OUTLINE PACKAGE




- NOTES: A. All linear dimensions are in millimeters.
 B. This drawing is subject to change without notice.
 C. Body dimensions do not include mold flash or protrusion.
 D. Falls within JEDEC MO-187

D (R-PDSO-G**)

PLASTIC SMALL-OUTLINE PACKAGE

8 PINS SHOWN




4040047/E 09/01

- NOTES: A. All linear dimensions are in inches (millimeters).
 B. This drawing is subject to change without notice.
 C. Body dimensions do not include mold flash or protrusion, not to exceed 0.006 (0.15).
 D. Falls within JEDEC MS-012

PW (R-PDSO-G**)

PLASTIC SMALL-OUTLINE PACKAGE

14 PINS SHOWN



- NOTES:
- All linear dimensions are in millimeters.
 - This drawing is subject to change without notice.
 - Body dimensions do not include mold flash or protrusion not to exceed 0,15.
 - Falls within JEDEC MO-153

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Mailing Address:

Texas Instruments
Post Office Box 655303
Dallas, Texas 75265