# NPN General Purpose Transistor

The MMBT2222AM3T5G device is a spin-off of our popular SOT-23 three-leaded device. It is designed for general purpose amplifier applications and is housed in the SOT-723 surface mount package. This device is ideal for low-power surface mount applications where board space is at a premium.

#### **Features**

- Reduces Board Space
- This is a Halide-Free Device
- This is a Pb-Free Device

#### **MAXIMUM RATINGS**

Rating	Symbol	Value	Unit
Collector - Emitter Voltage	V <sub>CEO</sub>	40	Vdc
Collector - Base Voltage	V <sub>CBO</sub>	75	Vdc
Emitter - Base Voltage	V <sub>EBO</sub>	6.0	Vdc
Collector Current – Continuous	I <sub>C</sub>	600	mAdc

### THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Total Device Dissipation FR-5 Board (Note 1) T <sub>A</sub> = 25°C Derate above 25°C	P <sub>D</sub>	265 2.1	mW mW/°C
Thermal Resistance, Junction-to-Ambient	$R_{ heta JA}$	470	°C/W
Total Device Dissipation Alumina Substrate, (Note 2) T <sub>A</sub> = 25°C Derate above 25°C	P <sub>D</sub>	640 5.1	mW mW/°C
Thermal Resistance, Junction-to-Ambient	$R_{\theta JA}$	195	°C/W
Junction and Storage Temperature	T <sub>J</sub> , T <sub>stg</sub>	-55 to +150	°C

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.


1

- 1. FR-5 =  $1.0 \times 0.75 \times 0.062$  in.
- 2. Alumina =  $0.4 \times 0.3 \times 0.024$  in. 99.5% alumina.



## ON Semiconductor®

http://onsemi.com



#### MARKING DIAGRAM



SOT-723 CASE 631AA STYLE 1



AA M Specific Device CodeDate Code

## ORDERING INFORMATION

Device	Package	Shipping <sup>†</sup>
MMBT2222AM3T5G	SOT-723 (Pb-Free)	

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

## **ELECTRICAL CHARACTERISTICS** (T<sub>A</sub> = 25°C unless otherwise noted)

Characteristic		Symbol	Min	Max	Unit
OFF CHARACTERISTICS					
Collector - Emitter Breakdown Voltage (I <sub>C</sub> =	10 mAdc, I <sub>B</sub> = 0)	V <sub>(BR)CEO</sub>	40	_	Vdc
Collector – Base Breakdown Voltage (I <sub>C</sub> = 10	) μAdc, I <sub>E</sub> = 0)	V <sub>(BR)CBO</sub>	75	_	Vdc
Emitter – Base Breakdown Voltage ( $I_E = 10 \mu$	vAdc, I <sub>C</sub> = 0)	V <sub>(BR)EBO</sub>	6.0	-	Vdc
Collector Cutoff Current (V <sub>CE</sub> = 60 Vdc, V <sub>EB</sub>	(off) = 3.0 Vdc)	I <sub>CEX</sub>	-	10	nAdc
Collector Cutoff Current	·)	I <sub>CBO</sub>		0.01 10	μAdc
Emitter Cutoff Current (V <sub>EB</sub> = 3.0 Vdc, I <sub>C</sub> = 0	0)	I <sub>EBO</sub>	-	100	nAdc
Base Cutoff Current (V <sub>CE</sub> = 60 Vdc, V <sub>EB(off)</sub>	= 3.0 Vdc)	I <sub>BL</sub>	-	20	nAdc
ON CHARACTERISTICS			1		
$\begin{array}{l} \text{DC Current Gain} \\ (I_C=0.1 \text{ mAdc, } V_{CE}=10 \text{ Vdc}) \\ (I_C=1.0 \text{ mAdc, } V_{CE}=10 \text{ Vdc}) \\ (I_C=10 \text{ mAdc, } V_{CE}=10 \text{ Vdc}) \\ (I_C=10 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } T_A \\ (I_C=150 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } T_A \\ (I_C=150 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } (I_C=150 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } (I_C=150 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } (I_C=500 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } (I_C=500 \text{ mAdc, } V_{CE}=10 \text{ Vdc, } (I_C=150 \text{ MAdc, } V_{CE}=10 \text{ Vdc, } (I_C=$	lote 3) Note 3)	h <sub>FE</sub>	35 50 75 35 100 50 40	- - - - 300 - -	-
Collector – Emitter Saturation Voltage (Note $(I_C = 150 \text{ mAdc}, I_B = 15 \text{ mAdc})$ $(I_C = 500 \text{ mAdc}, I_B = 50 \text{ mAdc})$	3)	V <sub>CE(sat)</sub>	- -	0.3 1.0	Vdc
Base – Emitter Saturation Voltage (Note 3) ( $I_C$ = 150 mAdc, $I_B$ = 15 mAdc) ( $I_C$ = 500 mAdc, $I_B$ = 50 mAdc)		V <sub>BE(sat)</sub>	0.6	1.2 2.0	Vdc
SMALL-SIGNAL CHARACTERISTICS					
Current – Gain – Bandwidth Product (Note 4) $(I_C = 20 \text{ mAdc}, V_{CE} = 20 \text{ Vdc}, f = 6)$		f <sub>T</sub>	300	-	MHz
Output Capacitance (V <sub>CB</sub> = 10 Vdc, I <sub>E</sub> = 0, f = 1.0 MHz)		C <sub>obo</sub>	-	8.0	pF
Input Capacitance ( $V_{EB} = 0.5 \text{ Vdc}, I_{C} = 0, f = 0.5 \text{ Vdc}$	= 1.0 MHz)	C <sub>ibo</sub>	_	25	pF
Input Impedance $ \begin{aligned} \text{(I}_{C} &= 1.0 \text{ mAdc, V}_{CE} = 10 \text{ Vdc, f} = \\ \text{(I}_{C} &= 10 \text{ mAdc, V}_{CE} = 10 \text{ Vdc, f} = \end{aligned} $		h <sub>ie</sub>	2.0 0.25	8.0 1.25	kΩ
Voltage Feedback Ratio $ \begin{array}{l} \text{(I}_{C}=\text{1.0 mAdc, V}_{CE}=\text{10 Vdc, f} = \\ \text{(I}_{C}=\text{10 mAdc, V}_{CE}=\text{10 Vdc, f} = \\ \end{array} $		h <sub>re</sub>	_ _	8.0 4.0	X 10 <sup>-4</sup>
$\begin{aligned} &\text{Small}-\text{Signal Current Gain} \\ &\text{(I}_{\text{C}}=1.0 \text{ mAdc, V}_{\text{CE}}=10 \text{ Vdc, f}=1.0 \text{ kHz)} \\ &\text{(I}_{\text{C}}=10 \text{ mAdc, V}_{\text{CE}}=10 \text{ Vdc, f}=1.0 \text{ kHz)} \end{aligned}$		h <sub>fe</sub>	50 75	300 375	-
Output Admittance ( $I_C$ = 1.0 mAdc, $V_{CE}$ = 10 Vdc, f = ( $I_C$ = 10 mAdc, $V_{CE}$ = 10 Vdc, f =		h <sub>oe</sub>	5.0 25	35 200	μmhos
Collector Base Time Constant (I <sub>E</sub> = 20 mAdc, V <sub>CB</sub> = 20 Vdc, f = 31.8 MHz)		rb, C <sub>c</sub>	_	150	ps
Noise Figure ( $I_C$ = 100 $\mu Adc$ , $V_{CE}$ = 10 Vdc,	$R_S = 1.0 \text{ k}\Omega, f = 1.0 \text{ kHz}$	NF	-	4.0	dB
SWITCHING CHARACTERISTICS					
Delay Time	(V <sub>CC</sub> = 30 Vdc, V <sub>BE(off)</sub> = −0.5 Vdc,	t <sub>d</sub>	-	10	ns
Rise Time	$I_{\rm C}$ = 150 mAdc, $I_{\rm B1} \stackrel{?}{=}$ 15 mAdc)	t <sub>r</sub>	-	25	113
Storage Time	(V <sub>CC</sub> = 30 Vdc, I <sub>C</sub> = 150 mAdc,	t <sub>s</sub>	-	225	ns
Fall Time	$I_{B1} = I_{B2} = 15 \text{ mAdc}$	t <sub>f</sub>	_	60	'''

Pulse Test: Pulse Width ≤ 300 μs, Duty Cycle ≤ 2.0%.
 f<sub>T</sub> is defined as the frequency at which |h<sub>fe</sub>| extrapolates to unity.

### **SWITCHING TIME EQUIVALENT TEST CIRCUITS**




Figure 1. Turn-On Time

Figure 2. Turn-Off Time




Figure 3. DC Current Gain




Figure 4. Collector Saturation Region




Figure 5. Turn - On Time




Figure 6. Turn-Off Time




Figure 7. Frequency Effects




Figure 8. Source Resistance Effects




Figure 9. Capacitances




Figure 10. Current-Gain Bandwidth Product




Figure 11. "On" Voltages

Figure 12. Temperature Coefficients


50

100 200

500

## PACKAGE DIMENSIONS

SOT-723 CASE 631AA ISSUE D



NOTES:


- DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
- CONTROLLING DIMENSION: MILLIMETERS.
  MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL
- DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS

	MILLIMETERS		
DIM	MIN	NOM	MAX
Α	0.45	0.50	0.55
b	0.15	0.21	0.27
b1	0.25	0.31	0.37
O	0.07	0.12	0.17
D	1.15	1.20	1.25
Е	0.75	0.80	0.85
е	0.40 BSC		
ΗE	1.15	1.20	1.25
L	0.29 REF		
L2	0.15	0.20	0.25

STYLE 1: PIN 1. BASE

EMITTER EMITTER
 COLLECTOR

#### RECOMMENDED **SOLDERING FOOTPRINT\***



\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor and 📖 are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. arising out of the application or use of any product or circuit, and specification scan and do vary in different applications and actual performance may vary over time. All operating parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

#### **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA **Phone**: 303–675–2175 or 800–344–3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free USA/Canada

Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative