

DATA SHEET

BFT25A

NPN 5 GHz wideband transistor

Product specification
File under Discrete Semiconductors, SC14

December 1997

NPN 5 GHz wideband transistor

BFT25A

FEATURES

- Low current consumption (100 μ A – 1 mA)
- Low noise figure
- Gold metallization ensures excellent reliability.


PINNING

PIN	DESCRIPTION
Code: V10	
1	base
2	emitter
3	collector

DESCRIPTION

The BFT25A is a silicon npn transistor, primarily intended for use in RF low power amplifiers, such as pocket telephones and paging systems with signal frequencies up to 2 GHz.

The transistor is encapsulated in a 3-pin plastic SOT23 envelope.



QUICK REFERENCE DATA

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
V_{CBO}	collector-base voltage	open emitter	–	–	8	V
V_{CEO}	collector-emitter voltage	open base	–	–	5	V
I_C	DC collector current		–	–	6.5	mA
P_{tot}	total power dissipation	up to $T_s = 165\text{ }^{\circ}\text{C}$; note 1	–	–	32	mW
h_{FE}	DC current gain	$I_C = 0.5\text{ mA}$; $V_{CE} = 1\text{ V}$	50	80	200	
f_T	transition frequency	$I_C = 1\text{ mA}$; $V_{CE} = 1\text{ V}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 500\text{ MHz}$	3.5	5	–	GHz
G_{UM}	maximum unilateral power gain	$I_C = 0.5\text{ mA}$; $V_{CE} = 1\text{ V}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 1\text{ GHz}$	–	15	–	dB
F	noise figure	$\Gamma = \Gamma_{opt}$; $I_C = 0.5\text{ mA}$; $V_{CE} = 1\text{ V}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 1\text{ GHz}$	–	1.8	–	dB
		$\Gamma = \Gamma_{opt}$; $I_C = 1\text{ mA}$; $V_{CE} = 1\text{ V}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 1\text{ GHz}$	–	2	–	dB

Note

1. T_s is the temperature at the soldering point of the collector tab.

NPN 5 GHz wideband transistor

BFT25A

LIMITING VALUES

In accordance with the Absolute Maximum System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
V _{CBO}	collector-base voltage	open emitter	–	8	V
V _{CEO}	collector-emitter voltage	open base	–	5	V
V _{EBO}	emitter-base voltage	open collector	–	2	V
I _C	DC collector current		–	6.5	mA
P _{tot}	total power dissipation	up to T _S = 165 °C; note 1	–	32	mW
T _{stg}	storage temperature		–65	150	°C
T _j	junction temperature		–	175	°C

THERMAL RESISTANCE

SYMBOL	PARAMETER	THERMAL RESISTANCE
R _{th j-s}	from junction to soldering point (note 1)	260 K/W

Note

1. T_S is the temperature at the soldering point of the collector tab.

CHARACTERISTICS

T_j = 25 °C unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
I _{CBO}	collector cut-off current	I _E = 0; V _{CB} = 5 V	–	–	50	nA
h _{FE}	DC current gain	I _C = 0.5 mA; V _{CE} = 1 V	50	80	200	
f _T	transition frequency	I _C = 1 mA; V _{CE} = 1 V; T _{amb} = 25 °C; f = 500 MHz	3.5	5	–	GHz
C _{re}	feedback capacitance	I _C = I _c = 0; V _{CB} = 1 V; f = 1 MHz	–	0.3	0.45	pF
G _{UM}	maximum unilateral power gain (note 1)	I _C = 0.5 mA; V _{CE} = 1 V; T _{amb} = 25 °C; f = 1 GHz	–	15	–	dB
F	noise figure	Γ = Γ _{opt} ; I _C = 0.5 mA; V _{CE} = 1 V; T _{amb} = 25 °C; f = 1 GHz	–	1.8	–	dB
		Γ = Γ _{opt} ; I _C = 1 mA; V _{CE} = 1 V; T _{amb} = 25 °C; f = 1 GHz	–	2	–	dB





Note

1. G_{UM} is the maximum unilateral power gain, assuming S₁₂ is zero and

$$G_{UM} = 10 \log \left(\frac{|S_{21}|^2}{(1 - |S_{11}|^2)(1 - |S_{22}|^2)} \right) \text{dB.}$$

NPN 5 GHz wideband transistor





BFT25A



NPN 5 GHz wideband transistor



BFT25A

In Figs 6 to 9, G_{UM} = maximum unilateral power gain; MSG = maximum stable gain; G_{max} = maximum available gain.



NPN 5 GHz wideband transistor


BFT25A



f (MHz)	V_{CE} (V)	I_C (mA)
500	1	1

Noise Parameters

F_{min} (dB)	Γ_{opt}		$R_n/50$
	(mag)	(ang)	
1.9	0.79	4	2.5




NPN 5 GHz wideband transistor

BFT25A

f (MHz)	V _{CE} (V)	I _C (mA)
1000	1	1

Noise Parameters


F _{min} (dB)	Gamma (opt)		R _n /50
	(mag)	(ang)	
2	0.74	8	2.6



f (MHz)	V _{CE} (V)	I _C (mA)
2000	1	1


Noise Parameters

F _{min} (dB)	Gamma (opt)		R _n /50
	(mag)	(ang)	
2.4	0.72	26	1.7




NPN 5 GHz wideband transistor

BFT25A



$V_{CE} = 1\text{ V}; I_C = 1\text{ mA}.$
 $Z_0 = 50\ \Omega.$

Fig.15 Common emitter input reflection coefficient (S_{11}).




$V_{CE} = 1\text{ V}; I_C = 1\text{ mA}.$

Fig.16 Common emitter forward transmission coefficient (S_{21}).


NPN 5 GHz wideband transistor

BFT25A



$V_{CE} = 1\text{ V}; I_C = 1\text{ mA}.$

Fig.17 Common emitter reverse transmission coefficient (S_{12}).



$V_{CE} = 1\text{ V}; I_C = 1\text{ mA}.$
 $Z_0 = 50\ \Omega.$

Fig.18 Common emitter output reflection coefficient (S_{22}).


NPN 5 GHz wideband transistor

BFT25A

PACKAGE OUTLINE

Plastic surface mounted package; 3 leads

SOT23



NPN 5 GHz wideband transistor

BFT25A

DEFINITIONS

Data Sheet Status	
Objective specification	This data sheet contains target or goal specifications for product development.
Preliminary specification	This data sheet contains preliminary data; supplementary data may be published later.
Product specification	This data sheet contains final product specifications.
Limiting values	
Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.	
Application information	
Where application information is given, it is advisory and does not form part of the specification.	

LIFE SUPPORT APPLICATIONS

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips for any damages resulting from such improper use or sale.