



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE1328 Integrated Circuit Module – Hybrid, Audio Power Amp50W 2 Power Supplies Required

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Maximum Supply Voltage, V_{CCmax} $\pm 50\text{V}$
 Collector Current, I_{Cmax} 7A
 Operating Case Temperature, T_C $+85^\circ\text{C}$
 Storage Temperature Range, T_{stg} -30° to $+100^\circ\text{C}$
 Thermal Resistance, Junction to Case, $R_{\theta JC}$ 1.7°C/W

Recommended Operating Conditions: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Recommended Operating Voltage, V_{CC} $\pm 35\text{V}$
 Load Resistance, R_L 8Ω

Electrical Characteristics: ($T_A = +25^\circ\text{C}$, $V_{CC} = \pm 35\text{V}$, $R_L = 8\Omega$, $R_g = 600\Omega$, $V_G = 26.4\text{dB}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Quiescent Current	I_{CCO}	$V_{CC} = \pm 42\text{V}$	-	50	100	mA
Output Power	$P_O(1)$	THD = 0.2%, $f = 20\text{Hz}$ to 20kHz	50	-	-	W
	$P_O(2)$	THD = 0.2%, $f = 1\text{kHz}$	-	60	-	W
	$P_O(3)$	$V_{CC} = \pm 42\text{V}$, THD = 0.2%, $f = 1\text{kHz}$	-	70	-	W
Total Harmonic Distortion	THD (1)	$P_O = 1\text{W}$ to 50W , $f = 20\text{Hz}$ to 20kHz	-	-	0.2	%
	THD (2)	$P_O = 1\text{W}$, $f = 1\text{kHz}$	-	0.03	-	%
Frequency Response	f	$P_O = 1\text{W}$, $+0\text{dB}$, -1dB	10 to 100k			Hz
Input Resistance	r_i	$P_O = 1\text{W}$, $f = 1\text{kHz}$	-	52	-	k Ω
Output Noise Voltage	V_{NO}	$V_{CC} = \pm 42\text{V}$, $R_g = 10\text{k}\Omega$ -	0.3	0.5	-	mV_{rms}
Midpoint Voltage	V_N	$V_{CC} = \pm 42\text{V}$	-70	-	+70	mV

Pin Connection Diagram (Front View)

