



No. C933B



2SK334

Silicon N-Channel Junction-Type Field Effect TR
FOR CONDENSER MICROPHONES

FEATURE

* Because it has an ultra-compact outline, sets can be made compact.

ABSOLUTE MAXIMUM RATINGS/ $T_a = 25^\circ\text{C}$		unit	
Drain-gate current	V_{DG0}	-20	V
Gate current	I_G	10	mA
Allowable power dissipation	P_D	100	mW
Junction temperature	T_j	125	$^\circ\text{C}$
Storage ambient temperature	T_{stg}	-40 ~ +125	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS/ $T_a = 25^\circ\text{C}$		min	typ	max	unit
Drain current	I_{DSS}^* $V_{DS} = 10\text{ V}, V_{GS} = 0\text{ V}$	60*		800*	μA


[$T_a = 25^\circ\text{C}, V_{CC} = 4.5\text{ V}, R_D = 680\ \Omega, C_{in} = 15\text{ pF}$, in a specified test circuit (conforming with application circuit)].

			min	typ	max	unit
Transmission loss	G_v			-5		dB
Transmission loss voltage-drop characteristics	ΔG_{vV} $V_{CC} = 4.5 \sim 1.5\text{ V}, f = 1\text{ kHz}$ $v_i = 10\text{ mV}$				-3	dB
Transmission loss frequency characteristics	ΔG_{vf} $f = 1\text{ k} \sim 110\text{ Hz}, v_i = 10\text{ mV}$				-1	dB
Input impedance	z_i $f = 1\text{ kHz}$	20				$\text{M}\Omega$
Output noise voltage	V_{NO} $v_i = 0, \text{A-curve}$				-110	dB


* 2SK334 is graded as follows by drain current I_{DSS} : (unit: μA)

60	N11	180	150	N12	300	250	N13	450	400	N14	800
----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----

Equivalent circuit









Case Outline 2025-TR
(unit: mm)







These specifications are subject to change without notice.

TOKYO SANYO ELECTRIC CO., LTD. SEMICONDUCTOR DIVISION
15-13 6-CHOME, SOTOKANDA, CHIYODA-KU, TOKYO 100, JAPAN



Sample application circuit: 2-wire system





Information furnished by SANYO is believed to be accurate and reliable. However, no responsibility is assumed by SANYO for its use, nor for any infringements of patents or other rights of third parties which may result from its use, and no license is granted by implication or otherwise under any patent or patent rights of SANYO.